



**The article is no longer in our assortment.**

### Features:

#### EUROLITE freeDMX AP Wi-Fi Interface

Wi-Fi DMX interface for apps & programs like Steinigke Light'J

- Wi-Fi DMX interface for wireless lighting control from your tablet or PC
- Receives the control signals via the network and transmits them to the DMX line via cable
- Works with iOS and Android devices
- The apps' online fixture library is continuously updated and already includes more than 300 Eurolite and Futurelight fixtures - easily add new ones via the fixture profile editor
- Configuration via integrated webservice
- Access point and infrastructure mode
- 1 DMX feed-through output
- Mounting kits for racks, desks and truss systems available as an option
- Can transmit up to 512 DMX channels
- Control via DMX; Light 'J app; Wi-Fi; Light Captain App; ArtNet
- 2.4 GHz license-free worldwide
- Operating range up to 60m in the open air
- Operating range up to 30m in buildings
- Built with NEUTRIK connector
- In connection with f.e. FreeStyler, DMXControl 3, PC\_DIMMER, Lightkey (MAC)
- Made in Germany
- For application areas such as: Clubs/dancing school; Wedding/gala/events; Stage; theater; mobile djs / entertainer
- Silent operation

#### Package contents

- 1 x device, 1 x external mains adapter, 4 x foot, 2 x user manual, 1 x antenna, 1 x declaration of conformity

### Logistic

### EUROLITE QuickDMX Wireless Transmitter

Compact wireless DMX transmitter 2.4 GHz

- User-friendly 3-pin XLR adapter (male) with swivel antenna
- Wireless DMX eliminates extensive cabling between DMX controller and the DMX-controlled units in lighting installations
- Due to GFSK modulation with 78 channels, interference-free operation also alongside other QuickDMX transceiver and wireless devices in the 2.4 GHz band (e.g. Wi-Fi and Bluetooth)
- 1 to 512 QuickDMX receivers can be controlled by each transmitter
- LED indication for functions
- Transceiver, to be used as transmitter or receiver
- Can transmit up to 512 DMX channels
- Control via QuickDMX; DMX; plug and play
- Operating range up to 400m
- Up to 6 transmitters can be operated in parallel without interference

#### Package contents

- 1 x device, 1 x user manual, 1 x declaration of conformity, 1 x external mains adapter, 1 x uSB cable

### EUROLITE QuickDMX Wireless Receiver

Compact wireless DMX receiver 2.4 GHz

- User-friendly 3-pin XLR adapter (female) with swivel antenna
- Wireless DMX eliminates extensive cabling between DMX controller and the DMX-controlled units in lighting installations
- Due to GFSK modulation with 78 channels, interference-free operation also alongside other QuickDMX transceiver and wireless devices in the 2.4 GHz band (e.g. Wi-Fi and Bluetooth)
- 1 to 512 QuickDMX receivers can be controlled by each transmitter
- LED indication for functions
- Transceiver, to be used as transmitter or receiver
- Can receive and process up to 512 DMX channels
- Control via QuickDMX; plug and play
- Operating range up to 400m
- Up to 6 transmitters can be operated in parallel without interference

#### Package contents

- 1 x device, 1 x user manual, 1 x declaration of conformity, 1 x external mains adapter, 1 x uSB cable

### Technical specifications:

---

Weight: 960 g

---

### EUROLITE freeDMX AP Wi-Fi Interface

Power supply: 100-240 V AC, 50/60 Hz  
12 V DC 1 A

---

IP classification: IP20

---

Wi-Fi: Standard: IEEE 802.11 b/g/n

---

DMX channels: Output 512

---

DMX input: 1 x 3-pin XLR (M) mounting version

---

DMX output: 1 x 3-pin XLR (F) mounting version

---

Control: DMX; Light´J app; Wi-Fi; Light Captain App; ArtNet

---

Range: Range up to 60m in the open air

---

	Range up to 30m in buildings
Frequency band:	2.4 GHz
Antenna gain:	2 dBi
Status LED:	Signal, pairing, link, channel source
Use of brands:	Built with NEUTRIK connector
Color:	Black
PC connect:	F.e. FreeStyler, DMXControl 3, PC_DIMMER, Lightkey (MAC)
Dimensions:	Width: 13 cm Depth: 11,5 cm Height: 4,1 cm
Weight:	650 g
Noise classification:	Class 0 (no noise at all)

### EUROLITE QuickDMX Wireless Transmitter

Power supply:	100-240 V AC, 50/60 Hz 5 V DC 1 A
IP classification:	IP20
Power connection:	Mains input via Coaxial power connector (M) mounting version power supply cord for USB A mains connection (provided)
DMX channels:	Output 512
DMX input:	1 x 3-pin XLR (M)
Control:	QuickDMX; DMX; plug and play
Range:	Range up to 400m
Carrier frequency:	2,4 GHz
Parallel mode:	Max. 6 transmitter
Modulation:	GFSK
Color:	Silver
Dimensions:	Length: 21,2 cm Diameter: Ø 1,8 cm
Weight:	150 g

### EUROLITE QuickDMX Wireless Receiver

Power supply:	100-240 V AC, 50/60 Hz
Pin configuration:	Inside + / outside -
IP classification:	IP20
Power connection:	Mains input via Coaxial power connector (M) mounting version power supply cord for USB A mains connection (provided)
DMX channels:	Input 512
DMX output:	3-pin XLR (F)
Control:	QuickDMX; plug and play
Range:	Range up to 400m
Carrier frequency:	2,4 GHz

Parallel mode:	Max. 6 transmitter
Modulation:	GFSK
Color:	Silver
Dimensions:	Length: 21,2 cm Diameter: Ø 1,8 cm
Weight:	160 g