



The article is no longer in our assortment.

Features:

EUROLITE freeDMX AP Wi-Fi Interface

Wi-Fi DMX interface for apps & programs like Steinigke Light'J

- Wi-Fi DMX interface for wireless lighting control from your tablet or PC
 - Receives the control signals via the network and transmits them to the DMX line via cable
 - Works with iOS and Android devices
 - The apps' online fixture library is continuously updated and already includes more than 300 Eurolite and Futurelight fixtures - easily add new ones via the fixture profile editor
 - Configuration via integrated webserver
 - Access point and infrastructure mode
 - 1 DMX feed-through output
 - Mounting kits for racks, desks and truss systems available as an option
 - Can transmit up to 512 DMX channels
 - Control via DMX; Light'J app; Wi-Fi; Light Captain App; ArtNet
 - 2.4 GHz license-free worldwide
 - Operating range up to 60m in the open air
 - Operating range up to 30m in buildings
 - Built with NEUTRIK connector
 - In connection with f.e. FreeStyler, DMXControl 3, PC_DIMMER, Lightkey (MAC)
 - Made in Germany
 - For application areas such as: Clubs/dancing school; Wedding/gala/events; Stage; theater; mobile djs / entertainer
 - Silent operation
- Package contents**
- 1 x device, 1 x external mains adapter, 4 x foot, 2 x user manual, 1 x antenna, 1 x declaration of conformity

Logistic

EUROLITE QuickDMX Wireless Transmitter

Compact wireless DMX transmitter 2.4 GHz

- User-friendly 3-pin XLR adapter (male) with swivel antenna
- Wireless DMX eliminates extensive cabling between DMX controller and the DMX-controlled units in lighting installations
- Due to GFSK modulation with 78 channels, interference-free operation also alongside other QuickDMX transceiver and wireless devices in the 2.4 GHz band (e.g. Wi-Fi and Bluetooth)
- 1 to 512 QuickDMX receivers can be controlled by each transmitter
- LED indication for functions
- Transceiver, to be used as transmitter or receiver
- Can transmit up to 512 DMX channels
- Control via QuickDMX; DMX; plug and play
- Operating range up to 400m
- Up to 6 transmitters can be operated in parallel without interference

Package contents

- 1 x device, 1 x user manual, 1 x declaration of conformity, 1 x external mains adapter, 1 x USB cable

EUROLITE QuickDMX Wireless Receiver

Compact wireless DMX receiver 2.4 GHz

- User-friendly 3-pin XLR adapter (female) with swivel antenna
- Wireless DMX eliminates extensive cabling between DMX controller and the DMX-controlled units in lighting installations
- Due to GFSK modulation with 78 channels, interference-free operation also alongside other QuickDMX transceiver and wireless devices in the 2.4 GHz band (e.g. Wi-Fi and Bluetooth)
- 1 to 512 QuickDMX receivers can be controlled by each transmitter
- LED indication for functions
- Transceiver, to be used as transmitter or receiver
- Can receive and process up to 512 DMX channels
- Control via QuickDMX; plug and play
- Operating range up to 400m
- Up to 6 transmitters can be operated in parallel without interference

Package contents

- 1 x device, 1 x user manual, 1 x declaration of conformity, 1 x external mains adapter, 1 x USB cable

Technical specifications:

Weight:	960 g
---------	-------

EUROLITE freeDMX AP Wi-Fi Interface

Power supply:	100-240 V AC, 50/60 Hz 12 V DC 1 A
IP classification:	IP20
Wi-Fi:	Standard: IEEE 802.11 b/g/n
DMX channels:	Output 512
DMX input:	1 x 3-pin XLR (M) mounting version
DMX output:	1 x 3-pin XLR (F) mounting version
Control:	DMX; Light´J app; Wi-Fi; Light Captain App; ArtNet
Range:	Range up to 60m in the open air

	Range up to 30m in buildings
Frequency band:	2.4 GHz
Antenna gain:	2 dBi
Status LED:	Signal, pairing, link, channel source
Use of brands:	Built with NEUTRIK connector
Color:	Black
PC connect:	F.e. FreeStyler, DMXControl 3, PC_DIMMER, Lightkey (MAC)
Dimensions:	Width: 13 cm Depth: 11,5 cm Height: 4,1 cm
Weight:	650 g
Noise classification:	Class 0 (no noise at all)

EUROLITE QuickDMX Wireless Transmitter

Power supply:	100-240 V AC, 50/60 Hz 5 V DC 1 A
IP classification:	IP20
Power connection:	Mains input via Coaxial power connector (M) mounting version power supply cord for USB A mains connection (provided)
DMX channels:	Output 512
DMX input:	1 x 3-pin XLR (M)
Control:	QuickDMX; DMX; plug and play
Range:	Range up to 400m
Carrier frequency:	2,4 GHz
Parallel mode:	Max. 6 transmitter
Modulation:	GFSK
Color:	Silver
Dimensions:	Length: 21,2 cm Diameter: Ø 1,8 cm
Weight:	150 g

EUROLITE QuickDMX Wireless Receiver

Power supply:	100-240 V AC, 50/60 Hz
Pin configuration:	Inside + / outside -
IP classification:	IP20
Power connection:	Mains input via Coaxial power connector (M) mounting version power supply cord for USB A mains connection (provided)
DMX channels:	Input 512
DMX output:	3-pin XLR (F)
Control:	QuickDMX; plug and play
Range:	Range up to 400m
Carrier frequency:	2,4 GHz

Parallel mode:	Max. 6 transmitter
Modulation:	GFSK
Color:	Silver
Dimensions:	Length: 21,2 cm Diameter: Ø 1,8 cm
Weight:	160 g