

FUTURELIGHT EX-6/32 controller

Programmable DMX controller

Réf. : 51834046

GTIN: 4026397166422



L'article n'est plus disponible.

Caractéristiques:

- For all DMX-projectors with up to 6 control channels
- 4 different addresses can individually be controlled
- Further devices can be connected with the same address and will run synchronically
- The number of devices connected with each address is unlimited
- 32 freely programmable chasers with up to 32 steps
- Joystick for manual mirror movement
- Fixture selection via fixture keys
- Program-Run for running all programs
- Program-Run also possible via random-function
- Strobe-button for strobe-function
- Segment-display and control-LEDs
- Sound-control via jack mono jack socket or built-in microphone
- Blackout
- 24 control channels
- Software-update possible via optional accessory
- For 483 mm rack mounting (19")

Logistique

EAN / GTIN: 4026397166422

Poids: 3,30 kg

Longueur: 0.55 m

Largeur: 0.21 m

Hauteur: 0.21 m

Données techniques:

Alimentation électrique:	230 V AC, 50 Hz
Puissance totale de raccordement:	6,00 W
Dimension:	Largeur : 48,3 cm Profondeur : 13,2 cm

	Hauteur : 8,9 cm
	via 12 V DC, 500 mA power unit included in the delivery
Number of control channels:	24
Sound-control:	via Line In RCA socket (min. 100 mV)
DMX512 output:	3-pin XLR connector
Dimensions (L x W x H):	483 x 132 x 90 mm
	Rack installation with 3 u
Weight:	2 kg

Contenu de la livraison:
