

OMNITRONIC PM-322 DJ mixer

PRO 2+1-channel DJ mixer

Art. No.: 10006816

GTIN: 4026397193459



The article is no longer in our assortment.

Features:

- 2 input channels, switchable phone/line with 3-way equalizer
- 1 separate DJ mic channel with input sensitivity control (gain), 2-fold tone control (bass, treble) and talkover selector
- Microphone input via 6.3 mm mono jack on the faceplate
- High-quality and super-smooth channel faders
- Super-smooth crossfader replaceable from above
- Headphones output adjustable via Cue Level control
- Additional Cue Split/Cue Mix switch
- Cue Split function: the Cue signal is on the one side of the headphones and the output signal on the other side
- Cue Mix function: the adjustable mix of Cue signal and output signal is on both sides of the headphones
- Mixing of the headphones signal possible via cue mixing fader
- Master out 10-fold LED level displays (L/R)
- Master control
- Rec Out independent from Master level for records with static level

Logistic

EAN / GTIN: 4026397193459

Weight: 2,50 kg

Length: 0.27 m

Width: 0.13 m

Height: 0.34 m

Technical specifications:

| | |
|--------------------|--------------------------------|
| Power consumption: | 4,50 W |
| Frequency range: | 20 - 20000 Hz |
| Dimensions: | Width: 17,8 cm Depth: 27 cm |

| | |
|------------------------|-------------------------|
| | Height: 8,5 cm |
| Weight: | 2,05 kg |
| Power supply: | 230 V AC, 50 Hz, |
| | via supplied power unit |
| Inputs: | 2 phono, 4 line, 1 mic |
| Minimum input voltage: | |
| Microphone: | 2 mV, 4 kohms |
| Phono: | 3 mV, 50 kohms |
| Line: | 200 mV, 6 kohms |
| Output voltage: | 4.5 V peak to peak |
| Outputs: | 1 master, 1 rec via RCA |
| Distortion: | <0.09 % |
| S/N ratio: | 60 dB |
| Talkover attenuation: | -14 dB |