

OMNITRONIC PM-444Pi 4-Channel DJ Mixer with Player & USB Interface

4-channel DJ mixer with Bluetooth, MP3 player and USB interface

Art. No.: 10006825

GTIN: 4026397704815



List price: 296.31 €

incl. 19% VAT.

Features:

- 4 input channels with gain control, LED level meter, 3-band equalizer, cue button and channel fader
- 1 DJ microphone channel with level control, 2-band equalizer, on/off and talkover switch
- Built-in USB audio interface allows playback of digital audio files from a computer (PC and Mac)
- Prefader listening to input channels and the master output via adjustable headphones output, with cue mix/split function
- Crossfader with assignment switches
- Master channel with level and balance control
- 10-digit stereo LED level meter
- Adjustable monitor output
- 7 line and 2 phono inputs via RCA jacks
- Balanced XLR and RCA outputs
- Additional recording output
- LCD display
- The device can be connected via USB to the PC
- (19") 48.3 cm rack installation 4 U
- Control via Bluetooth
- For application areas such as: Clubs/dancing school; Installation; mobile djs / entertainer; restaurants, bars and hotels

Package contents

- 1 x user manual, 1 x power cord, 1 x mixer, 1 x rCA cable, 1 x uSB cable

Logistic

EAN / GTIN: 4026397704815

Weight: 3,95 kg

Length: 0.49 m

Width: 0.22 m

Height: 0.14 m

Technical specifications:

| | |
|------------------------|---|
| Power supply: | 100-240 V AC, 50/60 Hz |
| Power consumption: | Max. 10 W |
| Protection class: | Protection class II |
| Power connection: | Mains input via C8 (M) "figure 8" mounting version power supply cord with Euro plug (provided) |
| Frequency range: | 20 - 20000 Hz |
| S/N ratio: | >60 dB |
| Impedance: | Input: Microphone 1 kOhm Input: line 1 kOhm Input: phono 1 kOhm |
| Gain: | Input: variable |
| Control: | Bluetooth |
| Bluetooth: | Version: 4.2 + EDR Profiles: A2DP, AVRCP |
| Bluetooth device name: | PM-444Pi |
| Housing color: | Black |
| Display type: | LCD display |
| Control elements: | Crossfader selector switch, Crossfader, source selector, power switch |
| Status LED: | Power, CUE, master level meter, chanal level meter |
| Connections: | Input: Microphone via 1 x 3-pin XLR/6.35mm jack (F) combination socket (mounting version) Input: line via 5 x stereo RCA Input: phono via 2 x stereo RCA Output: master via 2 x 3-pin XLR Output: master via 1 x stereo RCA Output: rec. via 1 x stereo RCA Output: headphones via 1 x 6.3 mm jack socket (stereo) mounting version |
| Channels: | Input chanel: 2 x stereo with line-phono switch via RCA, channel control via fader, 3-band tone control EQ -30dB to12dB at 80Hz/12kHz, gain control, CUE switch, Crossfader selector switch, source selector Input chanel: 1 x stereo with Line-line switch via RCA, channel control via fader, 3-band tone control EQ -30dB to12dB at 80Hz/12kHz, gain control, CUE switch Input chanel: 1 x stereo with Line-USB switch via RCA or USB, channel control via fader, 3-band tone control EQ -30dB to12dB at 80Hz/12kHz, gain control Microphon chanel: 1 x mono via Combination socket (XLR/jack), channel control via Rotary dial, 2-band tone control EQ -30dB to12dB at 70Hz/13kHz Master output: 1 x stereo via XLR or RCA, channel control via Rotary dial |

Headphones output: stereo via Jack, channel control via Rotary dial

| | |
|--------------------------|--|
| Music format: | MP3, WAV; WAV |
| USB port: | USB 2.0, Typ B Typ A |
| PC connect: | Via USB |
| Housing design: | (19") 48.3 cm rack installation 4 U |
| Dimensions: | Width: 48,3 cm Depth: 17,8 cm Height: 8,9 cm |
| Weight: | 3,50 kg |
| Audio player | |
| Available storage media: | USB devices max. 32GB (FAT 32) |
