

OMNITRONIC MRS-1402USB Recording Mixer

Compact audio mixer with 14 inputs and USB interface

Art. No.: 10040273

GTIN: 4026397513905



The article is no longer in our assortment.

Features:

- Built-in USB audio interface allows recordings and playback of digital audio files with a computer (PC and Mac)
- Full duplex USB port: simultaneous recording and playback possible
- 4 mono input channels with gain control, 3-way EQ, Low Cut and pan control
- 4 stereo input channels with 3-way EQ, level switch and balance control
- Adjustable stereo aux send output
- Tape input and output
- Separate main mix and control room outputs
- Headphones output
- +48 V phantom power, can be switched centrally
- Precise 4-digit stereo LED level display
- Operation via supplied power unit
- Rugged, compact metal housing

Logistic

EAN / GTIN: 4026397513905

Weight: 2,97 kg

Length: 0.43 m

Width: 0.30 m

Height: 0.08 m

Technical specifications:

Power supply:	230 V AC, 50 Hz
Power consumption:	28,00 W
Power connection:	Mains input via Coaxial power connector (M) mounting version power supply cord with AC adapter (provided)
Frequency range:	20 - 20000 Hz
USB port:	USB 2.0, Typ B

Dimensions:	Width: 27 cm Depth: 21,5 cm Height: 7,2 cm
Weight:	2,72 kg
Inputs/sensitivity:	
Mic, mono	0.5 mV, XLR bal.
Line In, mono	1 mV, 6.3 mm jack bal.
Line In, stereo	10 mV, 6.3 mm jack L/R
Tape In	100 mV, RCA L/R
Outputs/level:	
Main Out:	650 mV, 6.3 mm jack L/R unbal.
Control Room	2 V max. 6.3 mm jack L/R unbal.
Aux Send:	2 V, 6.3 mm jack unbal.
Tape Out	2 V, RCA L/R
Headphones	2 V, 6.3 mm jack unbal.
Distortion:	0.05 %
S/N ratio:	>74 dB
Tone control/channel:	
Treble:	±15 dB at 12 kHz
Middle:	±15 dB at 2.5 kHz
Bass:	±15 dB at 80 Hz
Phantom power:	+48 V