

OMNITRONIC LH-065 Active DI Box

1-channel DI box, active

Art. No.: 10355065

GTIN: 4026397194913



List price: 83.18 €

incl. 19% VAT.

Features:

- 1 high-impedance signal input via XLR or 6.3 mm jack connectors
- 1 low-impedance XLR output
- 6.35 mm jack input, and output
- Converts an unbalanced line input (e.g. instruments) into a balanced XLR output for connecting a mixer
- Switchable input attenuation: 0 dB, -20 dB, -40 dB
- Cables can be routed under the housing
- For application areas such as: Installation; mobile use; mobile djs / entertainer

Package contents

- 1 x device, 1 x user manual, 1 x battery

Logistic

EAN / GTIN: 4026397194913

Weight: 0,75 kg

Length: 0.23 m

Width: 0.16 m

Height: 0.10 m

Technical specifications:

Power connection:	Mains input via Coaxial power connector (M) mounting version power supply cord with AC adapter (provided)
Battery:	1 x 9.0 V E block 6F22 zinc carbon included
Frequency range:	10 - 30000 Hz
THD:	<0,5 % at 1 kHz
Impedance:	Input: 470 kOhm Output: 600 Ohm
Input attenuation:	0 dB, -20 dB, -40 dB; switchable

Control elements:	Groundlift selector
Connections:	Input: 1 x 3-pin XLR Input: 1 x 6.3 mm plug (unbal.) Link: 1 x 6.3 mm plug (unbal.) Output: line via 1 x 3-pin XLR
Max. level:	Output: +6 dBu
Dimensions:	Width: 15 cm Depth: 13 cm Height: 6 cm
Weight:	540 g