

## OMNITRONIC BMS-1C USB Condenser Broadcast Microphone Set

Broadcast kit with USB condenser microphone, table mount, pop filter and spider

Art. No.: 13000455

GTIN: 4026397689648



### Features:

- Ideal for podcasts, live streaming, video chats, vlogs, gaming and broadcasting
- USB microphone with cardioid pickup pattern and condenser capsule
- Professional studio quality with 192 kHz/24 bit resolution
- Noise is effectively minimized thanks to the included accessories in the kit
- Sample rate: 192 kHz
- Polar pattern: Cardioid
- Control via plug and play
- Compatible with Win 7, Win 10, OS X 10.9 or better
- For application areas such as: Homerecording and studios

### Logistic

EAN / GTIN: 4026397689648

Weight: 1,30 kg

Length: 0.41 m

Width: 0.23 m

Height: 0.07 m

### Technical specifications:

Type:	Studio microphone
Capsule type:	Condenser
Polar pattern:	Cardioid
Frequency range:	20 - 20000 Hz
Sensitivity:	-32 dB
Max. SPL:	120 dB
Phantom power:	5 V DC
Control:	Plug and play
Sample rate:	192 kHz

USB port:	Type B
Material:	Metal
Color:	Black
Weight:	1.05 kg
Operating system:	Win 7, Win 10, OS X 10.9 or better

### **Scope of delivery:**

---

- 1 x user manual
- 1 x USB cable
- 1 x stand
- 1 x windshield
- 1 x microphone
- 1 x holder
- 1 x filter