

OMNITRONIC UHF-502 Bodypack incl. 823-832MHz Lavalier (CH B orange) Art. No.: 13053523

Bodypack transmitter with lavalier microphone

GTIN: 4026397580747



List price: 58.91 €

incl. 19% VAT.

Features:

- Operation in the Duplex Gap 823-832 MHz
 - Pilot frequency squelch technology delete wireless RF interference
 - Easy and error-free synchronization between receiver and transmitter via infrared signal
 - Sensitivity adjustable
 - LED indicator for battery capacity
 - Belt clip
 - LCD display
 - Charge status indicator
- transmitter**
- Powered by a battery/battery pack
 - Operating range up to 50m with line-of-sight
 - UHF 823 - 832 MHz License-free and approved in large parts of Europe
- Microphone**
- Polar pattern: Cardioid
- Package contents**
- 1 x transmitter, 1 x microphone

Logistic

EAN / GTIN: 4026397580747
Weight: 0,22 kg
Length: 0.21 m
Width: 0.09 m
Heigth: 0.07 m

Technical specifications:

| | |
|---------------|----------------------------------|
| Type: | Bodypack with microphone |
| Display type: | LCD display |
| Display: | Charge status indicator , Chanal |
| Weight: | 140 g |

Transmitter

| | |
|----------------------|---|
| Type: | Pocket transmitter |
| Power connection: | Battery/battery pack |
| Battery: | 2 x Mignon (AA) (not included) |
| S/N ratio: | >90 dB |
| THD: | <1 % at 1 kHz |
| Range: | Range up to 50m with line-of-sight |
| Frequency band: | UHF 823 - 832 MHz |
| Frequency stability: | ± 0,001 % |
| RF power output: | 5 mW (LO); 10 mW (HI) |
| Modulation: | FM |
| Frequency selection: | 100 Switchable frequencies |
| Output voltage: | 5 V |
| Connections: | Input: Microphone via Mini XLR (M) 3-pin mounting version |
| Color code: | CH A= green, CH B= orange, |
| Switch: | On/off switch |
| Dimensions: | Width: 6,6 cm Depth: 2,2 cm Height: 10,8 cm |

Microphone

| | |
|------------------|-------------------------------------|
| Type: | Lavalier microphone |
| Power supply: | 2-10 V DC |
| Cable length: | 1 m |
| Capsule type: | Electret Size: Ø 5,2 mm x 9,7 mm |
| Polar pattern: | Cardioid |
| Frequency range: | 50 - 15000 Hz |
| S/N ratio: | >63 dB |
| Sensitivity: | -47 dB |
| Impedance: | 680 Ohm |
| Connections: | Output: 1 x Mini XLR (F) 3-pin |