

EUROLITE Set DMX Split 8X Splitter + transmitter + receiver

DMX splitter with one wireless DMX transmitter and a phantom powered wireless DMX receiver

Art. No.: 2000053

GTIN:



List price: 415.31 €

incl. 19% VAT.

Features:

EUROLITE DMX Split 8X Splitter

Splitter with 8 galvanically isolated outputs, 3/5-pin & QuickDMX XLR sockets

- DMX splitter for splitting one DMX input signal to 8 DMX outputs
- Input and outputs XLR 3-pin and 5-pin each
- Each DMX output with independent driver and status indicator
- Input and outputs galvanically isolated
- Input and outputs with a set of respective power supply and internal fuse
- Switchable termination resistor
- Control via DMX; QuickDMX via 5-pin XLR (M) mounting version (optional)
- (19") 48.3 cm rack installation 1 U

Package contents

- 1 x device, 1 x user manual, 1 x power cord

Logistic

EUROLITE QuickDMX Wireless Transmitter

Compact wireless DMX transmitter 2.4 GHz

- User-friendly 3-pin XLR adapter (male) with swivel antenna
- Wireless DMX eliminates extensive cabling between DMX controller and the DMX-controlled units in lighting installations
- Due to GFSK modulation with 78 channels, interference-free operation also alongside other QuickDMX transceiver and wireless devices in the 2.4 GHz band (e.g. Wi-Fi and Bluetooth)
- 1 to 512 QuickDMX receivers can be controlled by each transmitter
- LED indication for functions
- Transceiver, to be used as transmitter or receiver
- Can transmit up to 512 DMX channels

- Control via QuickDMX; DMX; plug and play
- Operating range up to 400m
- Up to 6 transmitters can be operated in parallel without interference

Package contents

- 1 x device, 1 x user manual, 1 x declaration of conformity, 1 x external mains adapter, 1 x uSB cable

EUROLITE QuickDMX Wireless receiver phantom-power

Compact wireless DMX receiver 2.4 GHz, phantom powered

- User-friendly 5-pin XLR adapter(female) with swivel antenna
- Wireless DMX eliminates extensive cabling between DMX controller and the DMX-controlled units in lighting installations
- Due to GFSK modulation with 78 channels, interference-free operation also alongside other QuickDMX transceiver and wireless devices in the 2.4 GHz band (e.g. Wi-Fi and Bluetooth)
- 1 to 512 QuickDMX receivers can be controlled by each transmitter
- LED indication for functions
- Transceiver, to be used as transmitter or receiver
- Requires 5 V phantom power for operation
- Can receive and process up to 512 DMX channels
- Control via DMX; QuickDMX; plug and play
- Operating range up to 400m
- Up to 6 transmitters can be operated in parallel without interference

Package contents

- 1 x device, 1 x user manual, 1 x declaration of conformity

Technical specifications:

Weight: 2,46 kg

EUROLITE DMX Split 8X Splitter

| | |
|--------------------|--|
| Power supply: | 100-240 V AC, 50/60 Hz |
| Power consumption: | 5 W |
| Power connection: | Mains input via IEC connector (M) mounting version power supply cord with safety plug (provided) |
| DMX input: | 1 x 3-pin XLR (M) mounting version 1 x 5-pin XLR (M) mounting version |
| DMX output: | 8 x 3-pin XLR (F) mounting version Separate (galvanic) with independent driver and status indicator 8 x 5-pin XLR (F) mounting version Separate (galvanic) with independent driver and status indicator 1 x 5-pin XLR (F) mounting version Bypass 1 x 3-pin XLR (F) mounting version Bypass |
| Control: | DMX; QuickDMX via 5-pin XLR (M) mounting version (optional) |
| Control elements: | Bypass/terminating resistor switch, power switch |
| Housing design: | (19") 48.3 cm rack installation 1 U |
| Dimensions: | Width: 48,3 cm Depth: 14,5 cm Height: 4,45 cm |

Weight: 2,22 kg

EUROLITE QuickDMX Wireless Transmitter

| | |
|--------------------|--|
| Power supply: | 100-240 V AC, 50/60 Hz 5 V DC 1 A |
| IP classification: | IP20 |
| Power connection: | Mains input via Coaxial power connector (M) mounting version power supply cord for USB A mains connection (provided) |
| DMX channels: | Output 512 |
| DMX input: | 1 x 3-pin XLR (M) |
| Control: | QuickDMX; DMX; plug and play |
| Range: | Range up to 400m |
| Carrier frequency: | 2,4 GHz |
| Parallel mode: | Max. 6 transmitter |
| Modulation: | GFSK |
| Color: | Silver |
| Dimensions: | Length: 21,2 cm Diameter: Ø 1,8 cm |
| Weight: | 150 g |

EUROLITE QuickDMX Wireless receiver phantom-power

| | |
|--------------------|---|
| Power supply: | 5 V DC |
| IP classification: | IP20 |
| Power connection: | Mains input via 5-pin XLR (W) connector |
| DMX channels: | Input 512 |
| DMX output: | 1 x 5-pin XLR (F) |
| Control: | DMX; QuickDMX; plug and play |
| Range: | Range up to 400m |
| Carrier frequency: | 2,4 GHz |
| Parallel mode: | Max. 6 transmitter |
| Modulation: | GFSK |
| Color: | Silver |
| Dimensions: | Length: 21,2 cm Diameter: Ø 1,8 cm |
| Weight: | 100 g |