



**The article is no longer in our assortment.**

### Features:

#### EUROLITE LED KLS-30 Compact Light Set

DMX LED spotlight set with 12 x 4in1 LED for mobile use

- Complete LED light set with four compact LED spots
- Crossbar with integrated DMX control unit
- Ultra-light ideally suited for mobile use
- Comes pre-assembled
- 3 QCL LEDs with 4 watts each per spot (RGBW)
- Movable and tiltable spotlights
- DMX-controlled operation or stand-alone operation with Master/Slave function
- 2, 3, 4, 6, 16, 20 or 24 DMX channels selectable
- Sound-control via built-in microphone, microphone sensitivity adjustable
- Supports QuickDMX - the wireless DMX-system from Eurolite
- Built-in phantom fed socket for QuickDMX receiver (see accessories)
- DMX512 control via regular DMX controller
- Via DMX, each spot can be individually controlled
- Functions: RGBW color mixture, color presets, built-in programs, strobe effect with variable speed, dimmer, sound-control, Master/Slave operation
- Addressing and setting via control panel with 4-digit LED display
- Suited for installation on a speaker stand (not included) or truss
- Black lacquered metal version with movable mounting bracket
- Ideal for bands, stages or solo entertainers
- Switch-mode power supply for operation between 100 and 240 volts
- The device is cooled by passive convection cooling
- Control via stand-alone; DMX; QuickDMX
- Preprogrammed in Light'J; LED PC-Control 512; EASY SHOW 1; Light Captain; EASY SHOW 2; EASY SHOW 3

### Logistic

- Flicker-free
- With a beam angle of 24°

### **EUROLITE QuickDMX Wireless receiver phantom-power**

Compact wireless DMX receiver 2.4 GHz, phantom powered

- User-friendly 5-pin XLR adapter(female) with swivel antenna
- Wireless DMX eliminates extensive cabling between DMX controller and the DMX-controlled units in lighting installations
- Due to GFSK modulation with 78 channels, interference-free operation also alongside other QuickDMX transceiver and wireless devices in the 2.4 GHz band (e.g. Wi-Fi and Bluetooth)
- 1 to 512 QuickDMX receivers can be controlled by each transmitter
- LED indication for functions
- Transceiver, to be used as transmitter or receiver
- Requires 5 V phantom power for operation
- Can receive and process up to 512 DMX channels
- Control via DMX; QuickDMX; plug and play
- Operating range up to 400m
- Up to 6 transmitters can be operated in parallel without interference

#### **Package contents**

- 1 x device, 1 x user manual, 1 x declaration of conformity

### **EUROLITE QuickDMX Wireless Transmitter**

Compact wireless DMX transmitter 2.4 GHz

- User-friendly 3-pin XLR adapter (male) with swivel antenna
- Wireless DMX eliminates extensive cabling between DMX controller and the DMX-controlled units in lighting installations
- Due to GFSK modulation with 78 channels, interference-free operation also alongside other QuickDMX transceiver and wireless devices in the 2.4 GHz band (e.g. Wi-Fi and Bluetooth)
- 1 to 512 QuickDMX receivers can be controlled by each transmitter
- LED indication for functions
- Transceiver, to be used as transmitter or receiver
- Can transmit up to 512 DMX channels
- Control via QuickDMX; DMX; plug and play
- Operating range up to 400m
- Up to 6 transmitters can be operated in parallel without interference

#### **Package contents**

- 1 x device, 1 x user manual, 1 x declaration of conformity, 1 x external mains adapter, 1 x USB cable

## **Technical specifications:**

Weight: 3,34 kg

### **EUROLITE LED KLS-30 Compact Light Set**

|                    |   |
|--------------------|---|
| Power supply:      | 100-240 V AC, 50/60 Hz  |
| Power consumption: | 50 W  |
| IP classification: | IP20  |
| Lamp type:         | LED lamp  |
| Cooling:           | Passive convection cooling  |
| Control:           | Stand-alone; DMX; QuickDMX  |
| Preprogrammed in:  | Light J; LED PC-Control 512; EASY SHOW 1; Light Captain; EASY SHOW 2; EASY SHOW 3 |

|                         |   |
|-------------------------|---|
| Projection:             | Flicker-free                                    |
| Beam angle:             | 24°   |
| Beam angle (1/2 peak):  | 24°   |
| Beam angle (1/10 peak): | 54°   |
| Housing color:          | Black   |
| Dimensions:             | Width: 45 cm<br>Depth: 12 cm<br>Height: 18,5 cm |
| Weight:                 | 3,10 kg   |
| DMX channels:           | 2/3/4/6/16/20/24                                |
| DMX connection:         | 3-pin XLR                                       |
| QuickDMX connection:    | 5-pin XLR                                       |
| Sound control:          | via built-in microphone                         |
| LED type:               | QCL 4 W   |
| Number of LEDs:         | 12  |
| Beam angle:             | 24°   |
| Dimensions (L x W x H): | 450 x 120 x 185 mm                              |
| Special product:        | Not designed for household room illumination    |
| Intended use:           | Show effect lighting                            |

#### **EUROLITE QuickDMX Wireless receiver phantom-power**

|                    |   |
|--------------------|---|
| Power supply:      | 5V DC                                   |
| IP classification: | IP20                                    |
| Power connection:  | Mains input via 5-pin XLR (W) connector |
| DMX channels:      | Input 512                               |
| DMX output:        | 1 x 5-pin XLR (F)                       |
| Control:           | DMX; QuickDMX; plug and play            |
| Range:             | Range up to 400m                        |
| Carrier frequency: | 2,4 GHz                                 |
| Parallel mode:     | Max. 6 transmitter                      |
| Modulation:        | GFSK                                    |
| Color:             | Silver                                  |
| Dimensions:        | Length: 21,2 cm<br>Diameter: Ø 1,8 cm   |
| Weight:            | 0,10 kg                                 |

#### **EUROLITE QuickDMX Wireless Transmitter**

|                    |  |
|--------------------|--|
| Power supply:      | 100-240 V AC, 50/60 Hz<br>5V DC 1000 mA  |
| IP classification: | IP20   |
| Power connection:  | Mains input via coaxial power connector (M)<br>mounting version power supply cord for USB A<br>mains connection (provided) |
| DMX channels:      | Output 512   |

|                    |                                       |
|--------------------|---------------------------------------|
| DMX input:         | 1 x 3-pin XLR (M)                     |
| Control:           | QuickDMX; DMX; plug and play          |
| Range:             | Range up to 400m                      |
| Carrier frequency: | 2,4 GHz                               |
| Parallel mode:     | Max. 6 transmitter                    |
| RF power output:   | 19 dBm                                |
| Modulation:        | GFSK                                  |
| Color:             | Silver                                |
| Dimensions:        | Length: 21,2 cm<br>Diameter: Ø 1,8 cm |
| Weight:            | 0,15 kg                               |