

## EUROLITE Set LED BC-1 6400K + Triangle base black

Disco effect light with socket

Art. No.: 2000274

GTIN:



### Features:

- Rotating decorative luminary with white LEDs
- E27 socket
- These dancing color-theatrics please the eye and the spirit
- Create kaleidoscopic effects
- Perfect for use in small discos, party rooms and even in children's rooms
- Disco feeling anywhere, in no time at all
- Plug & Play: just screw it in - ready!
- Switch-mode power supply, automatic power supply adaption between 100 and 240 Volts without power selector
- Hot restrike
- 3 LEDs 1 W high-power cold white (CW)
- Multi beam effect
- Control via stand-alone
- <p>EUROLITE Triangle Base black
- <h2 class="featureSatz">Design base with E-27 socket</h2>Distinctive base for 60 W lamp
- Can also be used with UV lamp
- Control via on/off switch at cable
- For application areas such as: Party room; decoration

### Logistic

### Technical specifications:

Weight: 0.38 kg

**OMNILUX LED BC-1 E-27 Beam Effect 6400K**

IP classification:	IP20
Voltage (lamps):	230 V
Nominal wattage:	5 W
Base:	E27
Lamp type:	LED lamp
Lamp specification:	Hot restrike
LED type:	3 x 1 W high-power cold white (CW)
Beam angle:	180°
Speed:	10 RPM , 360 °
Control:	Stand-alone
Color of light:	White
Color temperature:	6400K
Lead time:	1 s
Construction:	Special
Operating temperature max.:	40° C
Operating temperature min.:	20° C
Burning position:	S180 (universal)
Lamp life:	20000 h
Luminous flux:	60 lm
Lamp current:	0.043 A
Dimensions (LxD):	130x80 mm
Housing color:	Clear
Weight:	0.09 kg
Special product:	Not designed for household room illumination
Intended use:	Show effect lighting

**EUROLITE Triangle Base black**

Power supply:	230 V AC, 50 Hz
Power consumption:	Max. 60 W
Power connection:	Fixed power supply cord with Euro plug
Cable construction:	2 x 0.75 mm <sup>2</sup> H03VVH2-F
Cable length:	Approx. 1.8 m
Base:	E27
Control:	On/off switch at cable
Color:	Black
Dimensions:	Width: 15 cm Depth: 15 cm Height: 10 cm
Weight:	0.29 kg

## Scope of delivery:

---

1 x device  
1 x user manual