

RELACART Set UR-260D Bodypack with HM-600S Headset and Lavalier

Art. No.: 20000941

GTIN: 4026397710953



The article is no longer in our assortment.

Features:

RELACART UR-260D 2-channel UHF Receiver 823-832 + 863-865 MHz

Diversity wireless receiver with DSP for microphone modeling and PC software

- 2-channel multifrequency wireless receiver with 24-bit processor for high-end audio quality
- Integrated MagicEQ enables amazing microphone modeling of hand-held microphones
- Choose from 7 presets based on popular microphone models (e835, beta58, e935, D5, SM57, N/D767a, SM58) and 3 user-definable presets
- Integrated Feedback Killer effectively eliminates feedback, providing maximum gain and increased clarity on every microphone
- DSP programming and management via Ethernet port and intuitively operated PC software
- High-quality antenna diversity reception
- 10 groups with 90 fixed frequencies within 11 MHz switching bandwidth
- Pilot frequency squelch technology delete wireless RF interference
- Automatic frequency scan (AFS) finds interference-free channels
- Easy and error-free synchronization between receiver and transmitter via infrared signal
- Multiple units can be linked with network cables
- Lock function for prevents undesired changes to settings
- 2 detachable BNC antennas allow for use with the R-14D antenna divider
- Rugged metal housing
- (19") 48.3 cm rack installation possible 1 U
- Digital signal processor 96kHz, 24 bit
- Operating range up to 80m
- UHF 863 - 865 MHz License-free and approved in Europe
- UHF 823 - 832 MHz License-free and approved in large parts of Europe
- Up to 9 transmitters can be operated in parallel without interference
- Multicolor LCD display

Logistic

EAN / GTIN: 4026397710953

Weight: 4,50 kg

Length: 0.00 m

Width: 0.00 m

Height: 0.00 m

- The device can be connected via RJ-45 (F) mounting version to the PC in connection with RELACART Magic EQ software
 - Desktop console housing
- Package contents**
- 1 x receiver, 2 x antenna, 1 x external mains adapter, 1 x jack cable, 2 x mounting bracket, 6 x screw, 1 x user manual, 1 x declaration of conformity

RELACART UT-222 Bodypack with HM-600S Headset

Bodypack transmitter with PLL multifrequency transmitter, 823-832 + 863-865 MHz

- Durable aluminum alloy housing, applicable for touring
- Pilot frequency squelch technology delete wireless RF interference
- 10 groups with 90 fixed frequencies within 11 MHz switching bandwidth
- Easy and error-free synchronization between receiver and transmitter via infrared signal
- Adjustable input gain
- RF output power Hi/Low adjustable
- Lock function for prevents undesired changes to settings
- Up to 9 transmitters can be operated in parallel without interference

transmitter

- Operating range up to 80m
- UHF 823 - 832 MHz License-free and approved in large parts of Europe
- UHF 863 - 865 MHz License-free and approved in Europe
- OLED display

microphone

- Polar pattern: Omnidirectional
- For further information about this product, please refer to the Data Sheet under "Downloads"

Package contents

- 1 x transmitter, 1 x microphone, 1 x windshield, 1 x user manual, 1 x declaration of conformity

RELACART LM-C420 Lavalier unidirectional

Inconspicuous electret lavalier microphone

- For attaching to the user's tie, shirt or collar
- Polar pattern: Cardioid
- For application areas such as: Theater; product presentations and lectures

Package contents

- 1 x microphone, 1 x windshield

Technical specifications:

| | |
|---------|---------|
| Weight: | 2,63 kg |
|---------|---------|

RELACART UR-260D 2-channel UHF Receiver 823-832 + 863-865 MHz

| | |
|---------------------|---|
| Type: | Receiver |
| Power supply: | 100-240 V AC, 50/60 Hz 12V DC 1000 mA |
| Power consumption: | Max. 9 W |
| Power connection: | Mains input via coaxial power connector (M) mounting version power supply cord with AC adapter (provided) |
| Number of channels: | 2 |
| Frequency range: | 45 - 18000 Hz |
| S/N ratio: | >100 dB |
| THD: | <0,5 % at 1 kHz |

| | |
|----------------------|--|
| Network connection: | Protocol: Ethernet TCP/IP via 1x RJ-45 (F) mounting version |
| DSP: | Digital signal processor 96kHz, 24 bit |
| Range: | Range up to 80m |
| Frequency band: | UHF 863 - 865 MHz; UHF 823 - 832 MHz |
| Diversity: | Antenna diversity |
| Switching bandwidth: | 11 MHz |
| Frequency stability: | ± 0,0005 % |
| Parallel mode: | Max. 9 transmitter |
| Modulation: | FM |
| Frequency selection: | 90 switchable frequencies In 10 groups with up to 10 preset frequencies each |
| Display type: | Multicolor LCD display |
| Control elements: | Power switch, groundlift selector, menu, navigation keys |
| Connections: | Antenna via 2 x BNC (F) 8 V Output: microphone via 2 x 3-pin XLR (M) mounting version Output: line via 1 x 6.3 mm plug (unbal.) |
| Material: | Metal |
| Color: | Black |
| PC connect: | RELACART Magic EQ software via RJ-45 (F) mounting version |
| Housing design: | Desktop console housing (19") 48.3 cm rack installation possible 1 U |
| Dimensions: | Width: 41 cm Depth: 26 cm Height: 4,3 cm |
| Weight: | 2,40 kg |

RELACART UT-222 Bodypack with HM-600S Headset

| | |
|----------------------|--------------------------------------|
| Parallel mode: | Max. 9 transmitter |
| Weight: | 0,21 kg |
| Type: | Bodypack with microphone |
| Power supply: | 3V DC |
| Power connection: | Battery/battery pack |
| Battery: | 2 x Mignon (AA) (not included) |
| Gain: | 0 dB -6 dB -12 dB |
| Range: | Range up to 80m |
| Frequency band: | UHF 823 - 832 MHz; UHF 863 - 865 MHz |
| Switching bandwidth: | 11 MHz |
| RF power output: | 5 mW (LO); 10 mW (HI) |
| Modulation: | FM |
| Frequency selection: | 90 switchable frequencies |

| | |
|-------------------|--|
| | In 10 groups with up to 10 preset frequencies each |
| Display type: | OLED display |
| Control elements: | Transmitter power switch (high-low) |
| Connections: | Output: Mini XLR (M) 4-pin mounting version |
| Switch: | On/off/mute switch |
| Material: | Aluminum |
| Color: | Black |
| Dimensions: | Width: 6,6 cm Depth: 2,3 cm Height: 8,4 cm |
| Weight: | 0,174 kg |
| Type: | Headset microphone |
| Power supply: | 2-10V DC |
| Cable length: | 1,2 m |
| Capsule type: | Condenser Size: Ø 5 mm x 6 mm |
| Polar pattern: | Omnidirectional |
| Frequency range: | 50 - 18000 Hz |
| Sensitivity: | -47 dB |
| Impedance: | 1800 Ohm |
| Connector type: | Mini XLR (F) 4-pin |
| Color: | Skin-colored |
| Weight: | 0,028 kg |

RELACART LM-C420 Lavalier unidirectional

| | |
|-------------------|--|
| Type: | Lavalier microphone |
| Power supply: | 2-10V DC |
| Power connection: | Mains input via Mini XLR (F) 4-pin |
| Cable length: | 1,2 m |
| Capsule type: | Electret |
| Polar pattern: | Cardioid |
| Frequency range: | 60 - 12000 Hz |
| S/N ratio: | >59 dB |
| Sensitivity: | -42 dB |
| Impedance: | 1800 Ohm |
| Switch: | Without |
| Material: | Aluminum |
| Color: | Black |
| Dimensions: | Length: 2,80 cm Diameter: Ø 1,10 cm |
| Weight: | 0,02 kg |