

EUROLITE Dynamic Fog 1200 Fog Machine

1200 watt fogger with DMX

Art. No.: 51702040

GTIN: 4026397556049



Features:

- Compact fog machine with high output volume
- Ideal for accentuating light and laser beams
- Concentrated and steady fog output
- Adjustable timer with interval and duration
- Continuous output
- Fan grille with blue LED illumination, switchable
- Short warm-up time
- Output distance: Approx. 4 m
- With level indication
- Operates on water-based fluid
- Removable tank
- Control via DMX; wireless remote control; wired remote control
- Fixtures available for LED PC-Control 512; Light Captain
- With mounting bracket
- 4 digit 7-segment LED display
- For application areas such as: Clubs/dancing school; stage; theater; rental
- Application possibility: Standing; suspended

Logistic

EAN / GTIN: 4026397556049

Weight: 8,30 kg

Length: 0.50 m

Width: 0.34 m

Height: 0.27 m

Technical specifications:

Power supply: 230 V AC, 50 Hz

Power consumption: 1200 W

IP classification: IP20

Power connection:	Mains input via IEC connector (M) mounting version power supply cord with safety plug (provided)
Battery:	1 x 12 V 23AE alkaline manganese built-in
Warm-up time:	Approx. 3 min
Output volume:	Approx. 340 m³/min
Output distance:	Approx. 4 m
Tank capacity:	2.3 l water-based fluid removable tank
Fluid consumption:	Approx. 40 ml/min
DMX channels:	1
DMX input:	1 x 3-pin XLR (M) mounting version
DMX output:	1 x 3-pin XLR (F) mounting version
Control:	DMX; wireless remote control; wired remote control
Fixtures available for:	LED PC-Control 512; Light Captain
Carrier frequency:	433.92 MHz
Housing color:	Black
Attachment system:	Mounting bracket
Heater:	1210 W
Display type:	4 digit 7-segment LED display
Color:	Black
Dimensions:	Width: 31 cm Depth: 42.5 cm Height: 29 cm
Weight:	7.20 kg
Noise classification:	Class 3 (clearly perceptible sounds)
Cable length:	3 m

Scope of delivery:

- 1 x device
- 1 x user manual
- 1 x power cord
- 2 x remote control
- 1 x declaration of conformity
- 1 x container
- 1 x filter
- 1 x battery