

## EUROLITE LED IP FL-100 COB RGB 120° RC

Outdoor floodlight (IP65) with 100 W COB LED (RGB) and IR remote control

Art. No.: 51914614

GTIN: 4026397552973



**The article is no longer in our assortment.**

### Features:

- Add highlights to your house and garden
- Ideal LED luminary for indoor or outdoor use
- Weather-proof housing (IP65)
- Mounting bracket for permanent installation included
- Extremely compact housing in an appealing design
- Equipped with 1 COB RGB LED
- Beam reflection angle of 120°
- Ready for connection via power cord with safety-plug
- Automatic color change or manual program or color selection
- Built-in programs for color change and color fade
- Adjustable program speed and brightness
- Direct color selection for 15 preset colors + white
- Memory function for control programs via the Flash, Strobe, Fade and Smooth buttons of the IR remote control
- 1 LED 100 W COB (chip-on-board) 3in1 R/G/B (homogenous color mix)
- The device is cooled by passive convection cooling
- Control via stand-alone; IR remote control
- With a beam angle of 120°
- Suitable for outdoor use IP65
- Silent operation
- **remote control**
- Operating range up to 7m

### Logistic

EAN / GTIN: 4026397552973

Weight: 5,48 kg

Length: 0.40 m

Width: 0.31 m

Height: 0.15 m

## Technical specifications:

---

Power supply:	100-240 V AC, 50/60 Hz
Power consumption:	100 W
IP classification:	IP65
Protection class:	Protection class I
Power connection:	Fixed power supply cord with safety plug
Lamp type:	LED lamp
LED type:	1 x 100 W COB (chip-on-board) 3in1 R/G/B (homogenous color mix)
Cooling:	Passive convection cooling
Control:	Stand-alone; IR remote control
Beam angle (1/2 peak):	120°
Housing color:	Silver
Color:	Clear
Dimensions:	Width: 28.3 cm Depth: 9.8 cm Height: 38 cm
Weight:	5.08 kg
Noise classification:	Class 0 (no noise at all)
Range:	Range up to 7m
Special product:	Not designed for household room illumination
Intended use:	Show effect lighting

## Scope of delivery:

---

1 x spotlight  
1 x remote control  
1 x user manual