

## EUROLITE FD-12 DMX dimmer panel

DMX lighting controller 12 channels

Art. No.: 70063811

GTIN: 4026397298970



### Features:

- 12 channel faders with LED
- Fade time fader with LED for adjusting the step time
- Master fader with LED for adjusting the total output level
- Speed fader for adjusting the program-speed
- Flash button per channel and master-flash
- LED display of all modes
- 4 freely programmable programs with up to 84 steps each
- Controller comes with 4 pre-programmed chasers
- The programs and chasers can be called up individually or combined (CH1-2-3-4-PR-1-2-3-4)
- Dimmer: manual control of the channels via sliders
- Full On: all channels can be switched on together
- Blackout function
- Program speed adjustable via speed fader or tap sync button
- Sound-control via external signal or integrated microphone
- Only for professional use
- Sound to light via 6.3 mm jack
- Power supply via included power unit

### Logistic

EAN / GTIN: 4026397298970

Weight: 2,30 kg

Length: 0.53 m

Width: 0.23 m

Height: 0.15 m

### Technical specifications:

Power supply:	230 V AC, 50 Hz
Power consumption:	1.00 W
Battery:	1 x 9.0 V E block (not included)

Dimensions:	Width: 41.5 cm Depth: 15 cm Height: 7 cm
	via 9-15 V DC, 300 mA power unit included in the delivery
	or 1 standard 9 V battery
Battery life:	approx. 3 hours
Number of control channels:	12
Integrated chasers:	4
Free programs:	4 x 84 scenes
Sound-control:	via built-in microphone or via audio-input
Audio-input:	Jack
Audio-sensitivity:	0.1-1 V
DMX512 output:	3-pin XLR connector
Weight:	2 kg

### **Scope of delivery:**

---