

FUTURELIGHT DMX Split 6 Splitter CRMX

6-fold splitter and wireless DMX receiver (2.4 GHz) for truss and wall mounting

Art. No.: 70064822

GTIN: 4026397726329



Features:

- DMX splitter for splitting one DMX input signal to 6 DMX outputs
- Adaptive frequency hopping ensures interference-free operation in the 2.4 GHz band
- Input and outputs galvanically isolated
- Can transmit up to 512 DMX channels
- Each DMX output with active signal processing
- Control via DMX; CRMX by LumenRadio; W-DMX by wireless solution
- Operating range up to 500m with line-of-sight
- 2.4 GHz license-free worldwide
- Up to 10 transmitters can be operated in parallel without interference
- Ultra-low latency
- With Holder for wall mounting

Logistic

EAN / GTIN: 4026397726329
Weight: 1,60 kg
Length: 0.23 m
Width: 0.18 m
Heigh: 0.13 m

Technical specifications:

Power supply:	100-240 V AC, 50/60 Hz
Power consumption:	10 W
IP classification:	IP20
Protection class:	Protection class I
Power connection:	Mains input via IP T-Con (M) mounting version power supply cord with safety plug
Fuse:	5 x 20 mm, F 1 A fuse replaceable
DMX channels:	Output 512

DMX input:	3-pin XLR (M) mounting version
DMX output:	3-pin XLR (F) mounting version 6 x 3-pin XLR (F) mounting version separate (galvanic) with active signal processing
Control:	DMX; CRMX by LumenRadio; W-DMX by wireless solution
Range:	Range up to 500m with line-of-sight
Frequency band:	2.4 GHz
Parallel mode:	Max. 10 transmitter
Antenna gain:	5 dBi
Latency:	< 5 ms
Modulation:	GFSK
Housing color:	Black
Attachment system:	M10 thread Holder for wall mounting
Status LED:	DMX, pairing, power, level meter
Dimensions:	Length: 13.7 cm Width: 12.2 cm Height: 11.2 cm
Weight:	1.20 kg

Scope of delivery:

- 1 x device
- 1 x user manual
- 1 x power cord
- 1 x antenna
- 1 x mounting bracket
- 2 x strap
- 1 x declaration of conformity