

OMNITRONIC PM-3010B Pro DJ mixer

PRO 3+1-channel DJ mixer with matrix

Réf. : 10006851

GTIN: 4026397313055



L'article n'est plus disponible.

Caractéristiques:

- Matrix input assignment: each channel with routing facility of all input sources as desired
- 3 channels with gain control, 3-band equalizer, cue button, smooth and durable fader and 10-digit LED level meter
- 1 DJ microphone channel with 3-band equalizer, level control, on air and talkover selector
- Color illuminated rotary controls and rubber buttons
- Prefader listening to all input channels and the master output via adjustable headphones output, with cue mix/split function
- Replaceable crossfader with VCA technology for crossfading between input channels, with assignment switches, adjustable curve and reverse function
- Master control and stereo LED level meter
- Master level switchable 0.75 V or 1.5 V
- Separately controllable monitor and zone outputs
- Separately controllable session output to connect a further mixer
- 2 recording outputs, independent of the master and with on/off switch for DJ microphone signals
- Inputs: 4 x line (stereo RCA); 3 x phono/line (stereo RCA), switchable; 1 x DJ microphone (XLR/6.3 mm jack), 2 x microphone (6.3 mm jack) and 1 x headphones (6.3 mm jack)
- Outputs: 1 x master (stereo XLR/stereo RCA), 1 x zone (6.3 mm stereo jack, bal.), 1 x booth (stereo RCA), 2 x record (stereo RCA) and 1 x session (stereo RCA)
- Operation via supplied power unit

Logistique

EAN / GTIN: 4026397313055

Poids: 5,00 kg

Longueur: 0.47 m

Largeur: 0.28 m

Hauteur: 0.17 m

Données techniques:

Puissance totale de raccordement: 35,00 W

Plage de fréquence: 20 - 20000 Hz

| | |
|-------------------------------|--|
| Dimension: | Largeur : 34 cm Profondeur : 22 cm Hauteur : 11 cm |
| Poids: | 4,55 kg |
| Power supply: | 230 V AC, 50 Hz, via supplied power unit |
| Inputs: | |
| DJ microphone: | combined XLR/6.3 mm jack (1/4") (bal.) |
| MIC 1, 2: | 6.3 mm jack (1/4") (bal.) |
| Minimum input voltage: | 1 mV RMS |
| LINE/PHONO 1-3: | stereo RCA |
| Minimum input voltage: | 150 mV RMS (line), 3 mV RMS (phono) |
| AUX 1-4: | stereo RCA |
| Minimum input voltage: | 150 mV RMS |
| Outputs: | |
| MASTER: | stereo XLR/stereo RCA |
| Output voltage: | 0.75 V/1.5 V RMS (switchable) |
| ZONE: | 6.3 mm stereo jack |
| Output voltage: | 0.75 V RMS |
| BOOTH: | stereo RCA |
| Output voltage: | 0.75 V RMS |
| REC: | stereo RCA |
| Output voltage: | 0.75 V RMS |
| Headphones output: | 6.3 mm jack (min. 8 ohms) |
| Tone control (DJ microphone): | |
| 1 x high: | -12 dB to +12 dB/ 10 kHz, ± 1 dB |
| 1 x middle: | -12 dB to +12 dB/ 1 kHz, ± 1 dB |
| 1 x low: | -12 dB to +12 dB/ 100 Hz, ± 1 dB |
| Talkover attenuation: | -15 dB |
| Tone control (channel 1-3): | |
| 3 x high: | -26 dB to +12 dB/ 10 kHz, ± 1 dB |
| 3 x middle: | -26 dB to +12 dB/ 1 kHz, ± 1 dB |
| 3 x low: | -26 dB to +12 dB/ 100 Hz, ± 1 dB |
| S/N ratio: | >75 dB |
| Distortion: | 0.03% |
| Dimensions (WxHxD): | 340 x 220 x 110 mm |