

OMNITRONIC HRS-1002FX FX mixer

Table de mixage home recording à 10 canaux avec effet delay

Réf. : 10040206

GTIN: 4026397262827



L'article n'est plus disponible.

Caractéristiques:

- Low noise 10-channel mic/line mixer
- 2 mono inputs with XLR sockets, switchable +48V phantom power and balanced line inputs
- 4 stereo inputs with balanced 6.3 mm jack sockets
- Stereo inputs can also be operated mono
- 3-band EQ for all mono inputs
- Adjustable delay effect and effects display
- FX send control per channel for internal FX processor and/or as external send
- Peak LED per mono input
- Main mix output plus separate phones and stereo CD/tape output
- CD/tape input assignable to main mix or phones output
- 60-mm high-quality faders

Logistique

EAN / GTIN: 4026397262827

Poids: 2,50 kg

Longueur: 0.52 m

Largeur: 0.26 m

Hauteur: 0.10 m

Données techniques:

Puissance totale de raccordement:	25,00 W
Dimension:	Largeur : 19,5 cm Profondeur : 22 cm Hauteur : 4,3 cm
Poids:	1,90 kg
Power supply:	2 x 12 V AC, 50 Hz via included power unit
Inputs:	

2 mono	XLR
4 stereo	balanced 6.3 mm jacks
1 Tape In	RCA
Outputs:	
1 Master-Out	balanced 6.3 mm jacks
1 Aux Send:	balanced 6.3 mm jacks
1 Tape Out	RCA
1 Phones	balanced 6.3 mm jacks
1 Rec	RCA
Frequency range:	
Microphone:	10-60000 Hz, ± 3 dB
Mono:	10-60000 Hz, ± 3 dB
Stereo:	10-55000 Hz, ± 3 dB
Distortion:	0.01 %
S/N-ratio:	112 dB
Tone control/channel:	
Treble:	± 15 dB at 12 kHz
Middle:	± 15 dB at 2.5 kHz
Bass:	± 15 dB at 80 Hz
Dimensions (W x D x H):	195 x 220 x 43 mm