

## FUTURELIGHT WDS-1 Wirel. DMX transmitter

Transmitter for wireless data transmission

Réf. : 51834015

GTIN: 4026397449389



**L'article n'est plus disponible.**

### Caractéristiques:

- Wireless DMX is a technology to control many DMX devices without any cables or to bridge a distance between sender and receiver
- W-DMX is interference-free from other wireless devices in the 2.45 GHz band such as W-LAN
- W-DMX uses adaptive FHSS (Frequency Hopping Spread Spectrum) and TDMA (Time Division Multiple Access)
- One WDS-1 supports a single DMX512 universe with 512 DMX channels
- Larger systems can easily be adapted to support up to 8192 DMX channels (16 DMX512 universes)
- Up to 8192 receivers can be used in a W-DMX system
- Truss installation via Omega Clamp included in the delivery
- Peut recevoir et traiter jusqu'à 512 canaux DMX
- Peut envoyer jusqu'à 512 canaux DMX

### Logistique

EAN / GTIN: 4026397449389

Poids: 1,19 kg

Longueur: 0.21 m

Largeur: 0.10 m

Hauteur: 0.29 m

### Données techniques:

Puissance totale de raccordement:	3 W
Canaux DMX:	Entrée 512 Sortie 512
Dimension:	Largeur : 16,5 cm Profondeur : 4 cm Hauteur : 13,5 cm
Power supply:	230 V AC, 50 Hz

via 6-12 V DC, 1 A power unit included in the delivery

---

Number of control channels:	512 (1 DMX512 universe)
Max. number of receivers:	8192
DMX512 input:	5-pin and 3-pin XLR
Frequency:	2.450 GHz
Coverage:	1000 m (with line-of-sight)
Dimensions (L x W x H):	135 x 165 x 40 mm
Weight:	1 kg

---