

EUROLITE freeDMX Wi-Fi Interface

USB DMX interface with Wi-Fi module - for EUROLITE Light'J app

Réf. : 51860125

GTIN: 4026397506587



L'article n'est plus disponible.

Caractéristiques:

- DMX interface with integrated Wi-Fi module for wireless control of DMX devices
- freeDMX allows control of DMX devices through smartphones or tablet PCs more flexible than ever - right now true for Eurolite KLS and Hybrids
- For mobile iOS and Android devices
- Download matching apps from the App Store and Google Play
- Applicable as USB DMX interface for controlling DMX devices with a computer
- Supports various DMX software applications
- Fully supported by FreeStyler as of version 3.37 (freeware)
- Input or output of 512 DMX channels
- Windows XP, Vista, 7 and 8, Linux OLA-OpenDMX.net
- 3-pin Neutrik XLR connectors for DMX IN/DMX OUT
- USB 2.0 port
- Status LEDs for Wi-Fi, USB, DMX IN and DMX OUT
- Supports firmware updates
- Driver and firmware updater available for download at www.eurolite.de
- Powered via included PSU

Logistique

EAN / GTIN: 4026397506587

Poids: 0,26 kg

Longueur: 0.16 m

Largeur: 0.12 m

Hauteur: 0.06 m

Données techniques:

Dimension: Largeur : 9,8 cm
Profondeur : 8,8 cm
Hauteur : 5,2 cm

Power supply: 5 V DC, 1.2 A

	via included PSU
Wi-Fi standard:	IEEE 802.11g/b/n
Frequency range:	2.4 GHz range (ISM), 11 channels
Übertragungstyp:	DDSS/OFDM
Data rate:	1-11 Mbps (802.11b), 6-54 Mbps (802.11g)
Antenna:	2 dBi
DMX512 output:	1 universe (512 channels)
DMX connectors:	3-pin XLR mounting socket, 3-pin XLR mounting plug, Neutrik
USB port:	USB 2.0, type B
Dimensions (w/o antenna):	L 98 x W 88 x H 52 mm
Weight:	350 g