

## OMNITRONIC MPZ-500 PA mixing amplifier

Amplificateur mélangeur (système de sonorisation) 4 zones, zones commutables, 500 W RMS

Réf. : 80709750

GTIN: 4026397220766



**L'article n'est plus disponible.**

### Caractéristiques:

- Comfortable control of your PA speakers via 4-zone technology
- 4 PA zone outputs, independently switchable on the front panel
- Master PA output (70 V and 100 V)
- Output for low-impedance speakers (4-16 ohms)
- 3 microphone inputs (6.3 mm jack, unbal.) with separate level controls
- Microphone input 3 with adjustable priority circuit
- 3 line inputs (stereo RCA) with separate level controls
- 1 line output (stereo RCA)
- Chime, switchable
- Treble and bass control for the output signal
- 7-fold LED level display
- Master control for the output signal
- Fan-cooled
- Protection circuits with LED indication: over current, short circuit, turn-on delay
- Rack installation, brackets detachable

### Logistique

EAN / GTIN: 4026397220766

Poids: 17,60 kg

Longueur: 0.56 m

Largeur: 0.48 m

Hauteur: 0.20 m

### Données techniques:

Alimentation électrique:	230 V AC, 50 Hz
Puissance de sortie:	500 W RMS
Plage de fréquence:	80 - 16000 Hz
Sortie de la zone:	4 zones commutables
Dimension:	Largeur : 48,3 cm

Profondeur : 38,5 cm  
Hauteur : 13,35 cm

---

Output power:	500 W RMS
Output type:	70 V, 100 V or 4-16 ohms
Output current:	
70 V	7 A
100 V	5 A
Mic input:	5 mV, 600 ohms
Line input:	300 mV, 10 kohms
Output connectors:	Screw connectors, terminal block
Distortion:	0.5 % (1 kHz)
S/N ratio:	
Aux:	85 dB
Mic:	75 dB
Dimensions:	483 x 385 x 138 mm
Weight:	22 kg

---