

OMNITRONIC Amplificateur PA PAP-60

Amplificateur PA, 60 W RMS

Réf. : 80709804

GTIN: 4026397582055



L'article n'est plus disponible.

Description:

Reliable amplifier

The Omnitronic PAP-60 ELA mixer amplifier is your reliable partner for ELA sound reinforcement systems. Thanks to its 19" format, it is ideal for both mobile and fixed installations.

Outputs for ELA loudspeakers with 70 V and 100 V audio carriers or 4-16- ? loudspeakers leave nothing to be desired. In addition to a line input, the PAP-60 also offers a loop-through output. Choose between XLR and 6.3 mm jack for both. So you're always flexible.

Protection

A fan protects the interior of your PAP-60 from overheating. In addition to a switch-on delay, it also features protection circuits against overload, short-circuit and DC voltage. In these cases, your loudspeakers are electrically isolated from the amplifier. Both the PAP-60 and your speakers are protected from damage.

Caractéristiques:

- 1 line input (optionally XLR or 6.3 mm jack)
- 1 feed-through output (optionally XLR or 6.3 mm jack)
- 70 V, 100 V or 4-16 ohms operation
- Master control
- LED indicators for power, signal, clip and fault
- Protective circuits: over load, short circuit, turn-on delay, over heating, DC offset protection
- Load detection and power control
- Rack installation
- (19") 48,3 cm installation en rack 2 HE

Logistique

EAN / GTIN: 4026397582055

Poids: 9,60 kg

Longueur: 0.54 m

Largeur: 0.47 m

Hauteur: 0.18 m

L'étendue des fournitures

- 1 x mode d'emploi, 1 x amplificateur

Données techniques:

Alimentation électrique:	230 V AC, 50 Hz
Puissance de sortie:	60 W RMS
Branchement électrique:	Fixe Câble d'alimentation à prise contact de protection
Plage de fréquence:	60 - 16000 Hz
Rapport signal/bruit:	>90 dB Line
Distorsion harmonique:	<0,5 % avec 1 kHz
Impédance:	Technologie PA 100 V; 4-16 Ohm
Commutation:	Class AB
Circuit de protection:	Démarrage progressif; Surchauffe; Surcharge; Court-circuit; Tension continue
État LED:	Signal, Power, Fault, Clip
Connexions:	Entrée: Line via 1 x Prise jack 6,3 mm (mono) version encastrable Entrée: Line via 1 x XLR 3 broches 0,8 V Sortie: Line via 1 x Prise jack 6,3 mm (mono) version encastrable Sortie: Line via 1 x XLR 3 broches
Conception du boîtier:	(19") 48,3 cm installation en rack 2 HE
Dimension:	Largeur : 48,3 cm Profondeur : 38,5 cm Hauteur : 8,9 cm
Poids:	7,90 kg