

OMNITRONIC CS-408 Powered Mixer

Universal powered stage mixer with 8 channels, 2 x 200 W/4 ohms

Art.n.: 10050050

GTIN: 4026397183283



Features :

- Low-noise 8-channel mic/line mixer and amplifier with 2 x 200 W/4 ohms output power
- Adjustable digital reverb
- 8 mono input channels (XLR and 6.3 mm jack) with gain control, 2-band EQ, pan and effect control
- Insert or direct out (6.3 mm jack) per input channel
- Aux send per channel for controlling external effectors
- Adjustable effect way for controlling external effect units (aux send/return)
- Tape input and output, switchable (stereo RCA)
- Adjustable headphones output (6.3 mm jack)
- +48V phantom power, can be switched centrally
- 2 x 7-band graphic equalizer for fine-tuned sound
- Precise 5-fold stereo LED meter
- 2 Speaker outputs
- Processore di segnale digitale

Logistica

EAN / GTIN: 4026397183283

Peso : 11,10 kg

Lunghezza : 0.35 m

Larghezza : 0.35 m

Altezza : 0.54 m

Dati tecnici :

Alimentazione elettrica: 115/230 V AC, 50/60 Hz

Potenza totale installata: 800,00 W

Potenza in uscita: Massimo 400 W
200 W RMS (4 Ohm)

Allacciamento elettrico:	Alimentazione dell'energia elettrica tramite dispositivi a freddo (M) versione da incasso cavo di alimentazione con spina di protezione (in dotazione)
Intervallo di frequenza:	10 - 60000 Hz microfono 10 - 60000 Hz Mono 10 - 55000 Hz Stereo
Rapporto segnale-rumore:	>112 dB
Distorsione armonica totale:	<0,01 % a 1 kHz
DSP:	Processore di segnale digitale
Commutazione:	Class AB
Equalizzatore:	Master: 2 x graphic equalizer 7-band
Misure:	Larghezza: 44 cm Profondità: 26 cm Altezza: 27,5 cm
Peso:	9,20 kg
Inputs:	
8 mono	XLR or balanced 6.3 mm jacks
1 Aux Return:	balanced 6.3 mm jack
1 Tape In	stereo RCA
Outputs:	
1 Main Out:	Speaker sockets
1 Headphones	balanced 6.3 mm jack
1 Aux Send:	balanced 6.3 mm jack
1 Tape Out	RCA
Tone control/channel:	
Treble:	±15 dB at 12 kHz
Middle:	±15 dB at 2.5 kHz
Bass:	±15 dB at 80 Hz
Power output sine:	
Stereo 4 ohms	2 x 200 W

Contenuto della confezione: