

PSSO HSP-2800 MK2 SMPS Amplifier

Art.n.: 10451690

Amplificatore PA stereo in class H con alimentatore switching, 2 x 850 W RMS (8 Ohm), 2 x 1400 W RMS (4 Ohm)

GTIN: 4026397505917



L'articolo non è più disponibile.

Features :

- Stereo PA amplifier with class H circuitry
- Low weight and height due to integrated switch mode power supply
- Reliable power amp with high impulse stability for a wide range of applications (e.g. compact PAs, multi-way PAs, international concerts)
- Limiter and speaker switch-on delay
- 3 operating modes can be selected (stereo, parallel or bridged)
- 2 calibrated level controls for precise level adjustment
- Input sensitivity and limiter adjustable
- LED VU meter and LEDs for activated protective circuit (protect), overload (clip), and signal per channel
- LEDs for parallel and bridge mode
- Complete protection set against short-circuit, overheat, clipping, overload, DC voltage and VHF signals
- Highly efficient front-to-rear air routing
- Electronically balanced inputs via XLR mounting jacks, with XLR feed-through outputs
- Speaker outputs via lockable Speaker plugs and screw terminals
- Rugged steel chassis with aluminum front panel
- Rack installation with 2 units

Logistica

EAN / GTIN: 4026397505917

Peso : 14,80 kg

Lunghezza : 0.61 m

Larghezza : 0.57 m

Altezza : 0.18 m

Dati tecnici :

Alimentazione elettrica:	230 V AC, 50 Hz
Potenza totale installata:	1500,00 W 1/8 Power
Potenza in uscita:	2 x 850 W RMS (8 Ohm)

	2 x 1400 W RMS (4 Ohm)
Intervallo di frequenza:	20 - 20000 Hz
Commutazione:	Class H
Misure:	Larghezza: 48,3 cm Profondità: 50,5 cm Altezza: 8,9 cm
Peso:	12,90 kg
Power output (RMS):	
Stereo 4 ohms	2 x 1400 W
Stereo 8 ohms	2 x 850 W
8 ohms bridged	1 x 3000 W
Signal-to-Noise ratio:	>90 dB
Total harmonic distortion:	<0.1 %
Damping factor:	>300
Voltage gain:	38 dB
Slew rate:	>20 V/μsec
Crosstalk:	>70 dB
Input sensitivity:	32 dB/1.0 V/0.775 V, switchable
Input impedance:	20 kohms (balanced), 10 kohms (unbalanced)
Input connectors:	2 x XLR
Output connectors:	2 x Speaker, screw terminals, 2 x XLR feed-through output
Protection:	Overheat, overload, short-circuit, over-current, DC voltage, softstart, VHF signals
Cooling:	2 temperature-controlled fans, front-to-rear
Controls:	Power switch, input attenuators, mode switch stereo/parallel/bridged, input sensitivity
LED indicators:	parallel, bridge (globally), protect, clip, signal (per channel)
Construction:	Steel chassis, aluminum front panel
	Rack installation with 2 U