

OMNITRONIC HDA-6.5 Amplifier

3-channel amplifier 2 x 500 W + 900 W @ 4 ohms

Art.n.: 10452360

GTIN: 4026397245516



Descrizione :

Concerning sound aspects, flexibility is the key. The HDA 6.5 amplifier can definitely be called flexible. Via two crossover networks, satellite cabinets as well as the subwoofer can be set in a way that you are able to change from background music to hot party sound with a strong base. To keep everything clean the fan grill is very helpful, as taking it down is very easy.

Features :

- 2 x 300 W + 500 W @ 8 ohms
- 2 x 500 W + 900 W @ 4 ohms
- Low Cut switch on the rear panel
- Rotary control for adjusting the upper crossover frequency (Hi Cut) of the subwoofer
- 3 gain controls
- All operation modes controllable via LEDs, can be switched off
- Signal inputs via XLR female or terminal block
- Speaker connection via terminal block or speaker jack
- Many protection circuits for optimized equipment protection
- Forced fan cooling
- Very rugged housing
- Rack installation

Logistica

EAN / GTIN: 4026397245516

Peso : 26,50 kg

Lunghezza : 0,55 m

Larghezza : 0,54 m

Altezza : 0,14 m

Dati tecnici :

Alimentazione elettrica: 230 V AC, 50 Hz

Potenza in uscita: Massimo 1900 W

| | |
|-------------------------------|--|
| Intervallo di frequenza: | 20 - 20000 Hz |
| Misure: | Larghezza: 48,3 cm Profondità: 45 cm Altezza: 8,9 cm |
| Peso: | 25 kg |
| Power output sine: | |
| Stereo 4 ohms | 2 x 500 W + 900 W |
| Stereo 8 ohms | 2 x 300 W + 500 W |
| Damping factor: | >250 |
| Distortion factor: | 0.05 % |
| Signal-to-noise ratio: | >95 dB |
| Min. input sensitivity: | 0.775 V RMS |
| Input impedance: | 10 kohms (unbalanced), 20 kohms (balanced) |
| Output impedance: | >0.02 ohms |
| Slew rate: | 20 V/ μ sec |
| LED indicators (per channel): | Clip, Protect, Signal |
| Minimum mounting depth: | 470 mm |

Contenuto della confezione:
