

RELACART UT-200 Bodypack with HM-800S Headset

Trasmettitore tascabile con trasmettitore multifrequenza PLL, 823-832 + 863-865 MHz

Art.n.: 13055225

GTIN: 4026397612639



L'articolo non è più disponibile.

Features :

- Pocket transmitter for receiver WAM-400
- Durable aluminum alloy housing, applicable for touring
- Incl. headset microphone HM-800S
- Lavalier microphone LM-C400 optional
- Pilot tone technology (PLL) for interference-free operation
- 2 license-free frequency ranges: 823-832 MHz (Duplex Gap) and 863-865 MHz
- 10 groups with 90 fixed frequencies within 11 MHz switching bandwidth
- Infrared interface for easy and error-free synchronization with the receiver via infrared signal
- Operation range 80 meters
- LED for battery status, frequency, channel and group
- Mute function
- RF output power Hi/Low adjustable
- Long battery life for up to 11 hours continuous operation
- Operation via 2 x 1.5 V battery (type AA), not included
- License-free and approved in the EU (please check on a country-by-country basis)
- Direttività: Di forma sferica
- UHF 863 - 865 MHz registrazione e gratuita in Europa
- UHF 823 - 832 MHz Registrazione e gratuita in gran parte d'Europa

Logistica

EAN / GTIN: 4026397612639

Peso : 0,35 kg

Lunghezza : 0.29 m

Larghezza : 0.11 m

Altezza : 0.07 m

Dati tecnici :

Tipo:	Trasmettitore tascabile con microfono
Allacciamento elettrico:	Pila/Batteria ricaricabile (non in dotazione)
Tipo di capsula:	Condensatore

Direttività:	Di forma sferica
Pila:	2 x 1,5 V AA Mignon R06 zinco-carbone presente
Intervallo di frequenza:	45 - 18000 Hz
Banda di frequenza:	UHF 863 - 865 MHz; UHF 823 - 832 MHz
Selezione frequenza:	Frequenze commutabili
Interruttore:	Interruttori di accensione/spegnimento
Materiale:	Alluminio
Misure:	Larghezza: 6,6 cm Profondità: 2,3 cm Altezza: 8,4 cm
Peso:	0,18 kg
Transmitting frequencies:	90
	10 frequency banks with up to 10 preset frequencies each
Switching bandwidth:	11 MHz
Deviation:	±45 kHz
Modulation:	FM
Coverage:	80 m (with line-of-sight)
Connection:	4-pin mini XLR jack (supplies 5 V)
Current consumption:	110 mA
Headset microphone:	
Type:	Electret
Directivity pattern:	Omnidirectional
Sensitivity:	-47 dB
Impedance:	2.2 kohms
Power supply:	2-10 V DC
Connection:	cable with 4-pin mini XLR plug
Cable length:	100 cm
Capsule dimensions:	6 x 5 mm