

RELACART Récepteur Diversity In-Ear PM-160R

Récepteur sans fil stéréo In-Ear à technologie Diversity

Réf. : 13055215

GTIN: 4026397537055



Description:

The PM-160 is a sturdy in-ear monitoring system delivering outstanding sound for live music, theatre and voice applications. Diversity technology guarantees optimum reception quality without interference or dropouts. The system can be operated in mono and stereo mode. The bodypack receiver is 190 g light and offers perfect wearing comfort.

Caractéristiques:

- Stereo pocket receiver with 32 preset channels for in-ear monitoring
- Sturdy all-metal housing with soft-touch controls, applicable for touring
- Diversity technology for high reception quality
- 2 license-free frequency ranges: 823-832 MHz (Duplex Gap) and 863-865 MHz
- Pilot frequency squelch technology delete wireless RF interference
- OLED display for battery status, frequency and channel
- LEDs for antenna A/B, AF signal and stereo operation
- Stereo or mono/mix mode
- Balance (left, right) adjustable
- Lock function for prevents undesired changes to settings
- License-free and approved in large parts of the EU (please check on a country-by-country basis)
- A une portée de jusqu'à 80m par visibilité
- UHF 823-832 MHz sans inscription et sans frais dans une grande partie de l'Europe
- UHF 863-865 MHz sans inscription et sans frais en Europe

Logistique

EAN / GTIN: 4026397537055

Poids: 0,33 kg

Longueur: 0.29 m

Largeur: 0.12 m

Hauteur: 0.07 m

Données techniques:

Type:	Retour de scène in-ear
Puissance totale de raccordement:	0,525 W
Branchement électrique:	Pile/batterie (non incluse dans la livraison) Tramite
Batterie:	2 x Mignon (AA) (non incluse dans la livraison)
Nombre de canaux:	1
Plage de fréquence:	45 - 18000 Hz
Rapport signal/bruit:	>105 dB
Portée:	Jusqu'à 80m par visibilité
Bande de fréquences:	UHF 823-832 MHz; UHF 863-865 MHz
Diversity:	Antenna-Diversity
Bande passante:	11 MHz
Stabilité de fréquence:	± 0,0005 %
Modulation:	FM, Stéréo
Sélection de la fréquence:	32 fréquence commutable
Connexions:	Entrée: Line via 1 x Prise jack 3,5 mm (stéréo) version encastrable
Commutateur:	Commutateur marche/arrêt
Matériau:	Aluminium
Dimension:	Largeur : 6,6 cm Profondeur : 2,2 cm Hauteur : 11,8 cm
Poids:	0,16 kg

Contenu de la livraison:

- 1 x récepteur
- 1 x Casque
- 1 x Clip de fixation
- 1 x Mode d'emploi
- 1 x déclaration de conformité