

FUTURELIGHT CP-240 Controller

Compact DMX controller

Réf. : 51834265

GTIN: 4026397194227



L'article n'est plus disponible.

Caractéristiques:

- 240 control channels for 12 projectors with up to 20 channels
- 8 channel faders with two banks for direct control of 16 channels
- PAN/TILT encoders
- All channels freely assignable
- All channel faders and encoders can be inverted
- Fine PAN/TILT movements possible via fine button
- Fade Time fader for adjusting the step time
- Fade Time assignable to only PAN/TILT or all DMX channels
- 240 scenes on 30 banks can be programmed
- 30 programs with up to 8 scenes can be programmed
- 6 chasers with up to 240 scenes can be programmed
- Copy function for the scenes, programs and banks
- Blackout function
- Fogger button for direct fogger control
- Sound control via RCA socket
- Rack installation with 3 units

Logistique

EAN / GTIN: 4026397194227

Poids: 2,95 kg

Longueur: 0.59 m

Largeur: 0.20 m

Hauteur: 0.13 m

Données techniques:

Alimentation électrique:	230 V AC, 50 Hz
Puissance totale de raccordement:	5,00 W
Dimension:	Largeur : 48,3 cm Profondeur : 13,4 cm

	Hauteur : 8,9 cm
	via 9-12 V DC, 300 mA power unit included in the delivery
Number of control channels:	240
Integrated programs:	30 with 8 scenes each
Chasers:	6 x 240 scenes
Sound-control:	via built-in microphone or via audio-input
Audio-input:	RCA
Audio-sensitivity:	0.1-1 V
DMX512 output:	3-pin XLR connector with polarity selector
Dimensions (L x W x H):	483 x 134 x 90 mm
	Rack installation with 3 u
Minimum mounting depth:	170 mm
Weight:	2.5 kg

Contenu de la livraison: