

EUROLITE LED PC-Control 512

Logiciel de contrôle d'éclairage et interface USB pour la réalisation de spectacles professionnels

Réf. : 51860150

GTIN: 4026397420029



L'article n'est plus disponible.

Description:

LED PC-Control is the ideal DMX512 software for all DJ and Architectural applications or small/medium-sized projects. It manages all LED technology-based equipment and can control any type of standard DMX appliance. The software is the most user friendly and affordable solution for DMX lighting control.

Caractéristiques:

- Graphic and user-friendly live board for touchscreens and smartphones
- Remotely trigger scenes and programs via Wi-Fi with your smartphone or instantly change RGB colors of your LED lights and much more
- Générateur automatique de programmes avec effets Pan/Tilt et RVB
- Graphic patch editor for DMX fixture addressing
- Quick fixture profile editor with 3000 files (libraries) included
- Advanced Matrix editor to allow all LED configurations
- Multiple menu languages (e.g. French, English, German)
- Full RGB (W/A) color and dimmer management and rendering
- Graphic 2D edition of fixtures
- Colors, dimmer, speed, black out and pause can be managed in live mode
- Fade-in time between programs and scenes
- Multiple program triggers
- DMX output speed signal can be configured for perfect DMX line stability and full compatibility with any electronic fixtures (Mab, Break, Delay, frequency 1 to 45 Hz)
- Durable aluminum housing with mounting flange
- Peut envoyer jusqu'à 512 canaux DMX
- Commandé via DMX; SmartBoard DMX App
- L'appareil peut être connecté au PC via USB, Connecté à LED PC-Control 512

Logistique

EAN / GTIN: 4026397420029

Poids: 0,32 kg

Longueur: 0.20 m

Largeur: 0.14 m

Hauteur: 0.06 m

- Compatible avec Win XP, Win Vista, Win 7, OS X 10,3 ou mieux
- Vous trouverez de plus amples informations sur ce produit dans la rubrique « Téléchargements » de la fiche technique

Données techniques:

Alimentation électrique:	100-240 V CA, 50/60 Hz 5V CC 500 mA
Puissance totale de raccordement:	1 W
Branchement électrique:	Alimentation électrique via micro-USB (F) version encastrable câble d'alimentation pour raccordement au réseau USB A (inclus dans la livraison) Tramite
Canaux DMX:	Sortie 512
Sortie DMX:	XLR (F) 3 broches version encastrable
Commande:	DMX; SmartBoard DMX App
Port USB:	USB 2.0, type mini-USB (F) version encastrable
Couleur:	Noir
PC connect:	LED PC-Control 512 via USB
Dimension:	Largeur : 7 cm Profondeur : 9 cm Hauteur : 4,5 cm
Poids:	0,22 kg
Système d'exploitation:	Win XP, Win Vista, Win 7, OS X 10,3 ou mieux

Contenu de la livraison:

1 x Appareil
1 x bloc d'alimentation externe
1 x Câble USB
1 x CD
1 x télécommande
1 x Batterie