

EUROLITE Distributeur de vidéos 1in8 VSD-108

Amplificateur de distribution AV 8x

Réf. : 81013015

GTIN: 4026397279931



Description:

Television for everybody!

Since pictures have learned how to move, it is impossible to imagine a world without television. Whether for entertainment or information, TV, in spite of the Internet, enjoys great popularity. A fact, hotel or airport managers know all too well. That is why they place plenty of screens in their halls or waiting rooms, so people are distracted and forget that they are actually waiting. Normally, you need an AV receiver for each device, so the program you have chosen can be played back. But due to our VSD-108 (see also VSD 104; AVS 402/802), this is a thing of the past now. Simply plug in the AV source and the signal will be distributed on up to eight screens without any loss. It does not have to be complicated all the time!

Caractéristiques:

- Pour la distribution de signaux audio, vidéo composite et S-vidéo TV d'une source AV vers un grand nombre de moniteurs TV
- Câblez en série un grand nombre de téléviseurs tout en conservant la même qualité d'image et évitez l'achat de plusieurs récepteurs AV
- Amplificateur intégré pour une distribution sans perte des signaux vidéo
- Transmission du signal jusqu'à 50 mètres
- AUX In supplémentaire pour connecter une source de musique
- Pour des domaines d'application tels que: Restaurants, bars et hôtels

Données techniques:

Alimentation électrique: 100-240 V CA, 50/60 Hz

Logistique

EAN / GTIN: 4026397279931

Poids: 1,05 kg

Longueur: 0.35 m

Largeur: 0.13 m

Hauteur: 0.06 m

Puissance totale de raccordement:	6,00 W
Plage de fréquence:	20 - 100 Hz
Rapport signal/bruit:	>100 dB
Distorsion harmonique:	<0,05 % avec 1 kHz
Dimension:	Largeur : 28,2 cm Profondeur : 12,8 cm Hauteur : 5 cm
Poids:	0,90 kg
Video:	
1 x input:	1 Vpp/ 75 ohms, composite RCA
8 x outputs:	1 Vpp/ 75 ohms, composite RCA
Gain:	2 V, 1 V (terminated)/ 75 ohms
Return loss:	>18 dB
Video bandwidth:	>100 MHz
Audio:	
2 x inputs:	22 kohms, stereo RCA and 3.5 mm jack (1/8")
8 x outputs:	1 kohms, stereo RCA
Gain:	nominal 0 dB
Channel separation:	>75 dB

Contenu de la livraison: