

OMNITRONIC PM-202FX 2-Channel DJ Mixer with Filter, FX and Bluetooth

Art. No.: 10006865

DJ mixer with Bluetooth connectivity, bipolar filter and 6 sound effects

GTIN: 4026397731088



Features:

- Bluetooth signal routable to channel 1 and 2
- DJ microphone channel with level control and 2-band equalizer
- Crossfader with adjustable curve and reverse function
- Pre-fader listening to all input channels and the master output via adjustable stereo headphones output
- Master channel with level control and stereo LED level meter
- 4 line and 2 phono inputs via RCA jacks
- Additional recording output
- DJ filter LPF/HPF bipolar per channel
- Control via Bluetooth
- Bluetooth: operating range up to 15m
- Desktop console housing
- For application areas such as: Party room; mobile use; mobile djs / entertainer

Logistic

EAN / GTIN: 4026397731088

Weight: 2,75 kg

Length: 0.36 m

Width: 0.25 m

Height: 0.15 m

Technical specifications:

Power supply:	100-240 V AC, 50/60 Hz
Power consumption:	Max. 8 W
Protection class:	Protection class II
Power connection:	Mains input via C8 (M) "figure 8" mounting version power supply cord with Euro plug (provided)
Frequency range:	20 - 20000 Hz

S/N ratio:	>80 dB
THD:	<0.1 % at 1 kHz
DJ filter:	Per channel: LPF/HPF bipolar,
DJ-FX:	Master: CHORUS, REVERB, DELAY, FLANGER Master: WHA, PHASE,
Control:	Bluetooth
Bluetooth device name:	PM-202FX
Range:	Bluetooth: range up to 15m
Crosstalk:	>60 dB
Control elements:	Crossfader, Crossfade curve control, crossfade reverse switch, FX Parameter control, power switch
Status LED:	Power, master level meter
Connections:	Input: line/phono via 2 x stereo RCA Input: line via 2 x stereo RCA Input: microphone via 1 x 3-pin XLR (F) mounting version Input: antenna via 1 x SMA (F) mounting version Input: Earthing connection via 2 x screw terminal Output: master via 2 x 3-pin XLR (M) mounting version Output: master via 1 x stereo RCA Output: rec. via 1 x stereo RCA Output: headphones via 1 x 6.3 mm jack socket (stereo) mounting version Output: headphones via 1 x 3.5 mm jack (stereo) mounting version
Channels:	Input channel: 2 x stereo with Line-Line/Phono-Bluetooth switch via RCA, channel control via 60mm fader, 2-band tone control EQ, gain control, CUE switch Microphone channel: 1 x mono via XLR, channel control via rotary dial, 2-band tone control EQ Master output: 1 x stereo via XLR or RCA, channel control via rotary dial, balancecontrol Headphones output: stereo via jack, channel control via rotary dial, cue mix function Rec. output: stereo via RCA
Material:	Metal
Color:	Black
Housing design:	Desktop console housing
Dimensions:	Length: 30.5 cm Width: 19.0 cm Height: 11.0 cm
Weight:	2.18 kg
Cable length:	2.10 m detachable

Scope of delivery:

1 x mixer
 1 x power cord
 1 x antenna
 1 x RCA cable
 1 x user manual
 1 x declaration of conformity