

OMNITRONIC PM-422P 4-Channel DJ Mixer with Bluetooth & USB Player

4-channel DJ mixer with Bluetooth and MP3 player

Art. No.: 10006878 GTIN: 4026397653410











List price: 272.51 €

incl. 19% VAT.

Features:

- 4 input channels with gain control, LED level meter, 3-band equalizer, cue button and channel fader.
- DJ microphone channel with level control, 2-band equalizer, on/off and talkover switch
- Pre-fader listening to all input channels and the master output via adjustable stereo headphones output
- Crossfader with assignment switches and adjustable curve
- Master channel with level and balance control
- 10-digit stereo LED level meter
- Adjustable monitor output
- 10 line and 2 phono inputs via RCA jacks
- Balanced XLR and RCA outputs
- Record output, independent of the master
- Control via Bluetooth
- LCD display
- Operating range up to 10m
- Desktop console housing
- For application areas such as: Party room; mobile djs / entertainer; mobile use

Package contents

- 1 x mixer, 1 x user manual, 1 x power cord, 1 x rCA cable, 1 x declaration of conformity

Technical specifications:

Power supply:	100-240 V AC, 50/60 Hz
Power consumption:	25 W

Logistic

EAN / GTIN: 4026397653410

Weight: 4,17 kg Length: 0.37 m Width: 0.29 m Heigth: 0.13 m

Protection class:	Protection class II
Power connection:	Mains input via C8 (M) "figure 8" mounting version power supply cord with Euro plug (provided)
Control:	Bluetooth
Bluetooth:	Version: 4,2 + EDR Profiles: A2DP, AVRCP
Audio player:	USB + Bluetooth
Range:	Range up to 10m
Carrier frequency:	2,4 GHz
Display type:	LCD display
Control elements:	Audio player, Talkover, Crossfader selector switch, Crossfader, Crossfade curve switch
Status LED:	Chanal level meter, master level meter, CUE, ON AIR, power
Connections:	Input: line via 6 x stereo RCA
	Input: line/phono via 2 x stereo RCA
	Input: Microphone via 1 x 6.3 mm jack socket (mono) mounting version
	Input: Audio player via 1 x USB A (F) mounting version
	Output: master via 1 x stereo RCA
	Output: master via 2 x 3-pin XLR
	Output: rec. via 1 x stereo RCA Output: booth via 1 x stereo RCA
	Output: headphones via 1 x 6.3 mm jack socket
	(stereo) mounting version
Channels:	Input chanel: 1 x stereo with Line-line-player switch via RCA or player, channel control via fader, 3-band tone control EQ, gain control, CUE switch
	Input chanel: 1 x stereo with Line-line switch via RCA, channel control via fader, 3-band tone control EQ, gain control, CUE switch
	Input chanel: 2 x stereo with Line-Line/Phono switch via RCA, channel control via fader, 3-band tone control EQ, gain control, CUE switch
	Microphon chanal: 1 x mono via Jack, channel control via Rotary dial, 2-band tone control EQ, Talkover switch, ON AIR switch
	Master output: 1 x stereo via XLR or RCA, channel control via Rotary dial, balancecontrol
	Booth output: 1 x stereo via RCA, channel control via Rotary dial, Cue-mix-function
	Headphones output: 1 x stereo via Jack, channel control via Rotary dial
Music format:	MP3, WAV; WAV
USB port:	Тур А
Housing design:	Desktop console housing
Dimensions:	Length: 35 cm
	Width: 26,6 cm
	Height: 10,5 cm
Weight:	3,46 kg
Audio player	
Available storage media:	USB devices max. 32GB (FAT 32)