

OMNITRONIC PM-422P 4-channel DJ Mixer with Bluetooth & USB Player

4-channel DJ mixer with Bluetooth and MP3 player

Art. No.: 10006878

GTIN: 4026397653410











List price: 272.51 €

incl. 19% VAT.

Features:

- 4 input channels with gain control, LED level meter, 3-band equalizer, cue button and channel fader.
- DJ microphone channel with level control, 2-band equalizer, on/off and talkover switch
- Pre-fader listening to all input channels and the master output via adjustable stereo headphones output
- Crossfader with assignment switches and adjustable curve
- Master channel with level and balance control
- 10-digit stereo LED level meter
- Adjustable monitor output
- 10 line and 2 phono inputs via RCA jacks
- Balanced XLR and RCA outputs
- Record output, independent of the master
- Control via Bluetooth
- Operating range up to 10m
- LCD display
- Desktop console housing
- For application areas such as: Party room; mobile djs / entertainer; mobile use

Package contents

- 1 x mixer, 1 x user manual, 1 x power cord, 1 x RCA cable, 1 x declaration of conformity

Technical specifications:

Power supply:	100-240 V AC, 50/60 Hz
Power consumption:	25 W

Logistic

EAN / GTIN: 4026397653410

Weight: 4,17 kg Length: 0.37 m Width: 0.29 m Heigth: 0.13 m

Protection class:	Protection class II
Power connection:	Mains input via C8 (M) "figure 8" mounting version power supply cord with Euro plug (provided)
Control:	Bluetooth
Bluetooth:	Version: 4,2 + EDR Profiles: A2DP, AVRCP
Bluetooth device name:	PM-422P
Audio player:	USB + Bluetooth
Range:	Range up to 10m
Carrier frequency:	2,4 GHz
Housing color:	Black
Display type:	LCD display
Control elements:	Audio player, talkover, crossfader selector switch, crossfader, crossfade curve switch
Status LED:	Chanal level meter, master level meter, CUE, ON AIR, power
Connections:	Input: line via 6 x stereo RCA Input: line/phono via 2 x stereo RCA Input: microphone via 1 x 6.3 mm jack socket (mono) mounting version
	Input: audio player via 1 x USB A (F) mounting version
	Output: master via 1 x stereo RCA Output: master via 2 x 3-pin XLR Output: rec. via 1 x stereo RCA Output: booth via 1 x stereo RCA
	Output: headphones via 1 x 6.3 mm jack socket (stereo) mounting version
Channels:	Input chanel: 1 x stereo with line-line-player switch via RCA or player, channel control via fader, 3-band tone control EQ, gain control, CUE switch
	Input chanel: 1 x stereo with line-line switch via RCA, channel control via fader, 3-band tone control EQ, gain control, CUE switch
	Input chanel: 2 x stereo with line-line/phono switch via RCA, channel control via fader, 3-band tone control EQ, gain control, CUE switch
	Microphon chanal: 1 x mono via jack, channel control via rotary dial, 2-band tone control EQ, talkover switch, ON AIR switch
	Master output: 1 x stereo via XLR or RCA, channel control via rotary dial, balancecontrol
	Booth output: 1 x stereo via RCA, channel control via rotary dial, cue mix function
	Headphones output: 1 x stereo via jack, channel control via rotary dial
Music format:	MP3, WAV; WAV
USB port:	Type A
Housing design:	Desktop console housing
Dimensions:	Length: 35 cm Width: 26,6 cm
	Height: 10,5 cm
Weight:	3,46 kg

Audio player	
Available storage media:	USB devices may 32GB (FAT 32)