

OMNITRONIC PM-311P DJ Mixer with Player

3-channel DJ mixer with integrated MP3 player

Art. No.: 10006879

GTIN: 4026397696578



Features:

- 3 input channels, switchable 2 x phono/line and 1 x USB/line
- All input channels with gain control, 3-band equalizer and cue button
- DJ microphone input with talkover selector, level control and 3-band equalizer
- Pre-fader listening (CUE) to the input channels and the master output via adjustable headphones output, with cue mix control
- Crossfader for crossfading between the phono/line channels
- 5-digit stereo LED level meter, switchable between master and PFL signal
- Additional recording output
- Desktop console housing
- For application areas such as: Party room; mobile djs / entertainer; mobile use

Logistic

EAN / GTIN: 4026397696578

Weight: 2,13 kg

Length: 0.34 m

Width: 0.24 m

Height: 0.12 m

Technical specifications:

Power supply:	230 V AC, 50 Hz 12V
Power consumption:	4.00 W
Protection class:	Protection class III
Power connection:	Mains input via coaxial power connector (M) mounting version power supply cord with AC adapter (provided)
Frequency range:	20 - 20000 Hz
S/N ratio:	>75 dB

THD:	<0.07 % at 1 kHz
Audio player:	USB
Housing color:	Black
Control elements:	Crossfader, source selector, talkover, power switch
Status LED:	Switchable master level meter, channel source, CUE, ON AIR
Connections:	<p>Input: line/phono via 2 x stereo RCA</p> <p>Input: line via 1 x stereo RCA</p> <p>Input: audio player via 1 x USB A (F) mounting version</p> <p>Input: microphone via 1 x 6.3 mm jack socket (mono) mounting version</p> <p>Output: master via 1 x stereo RCA</p> <p>Output: rec. via 1 x stereo RCA</p> <p>Output: headphones via 1 x 6.3 mm jack socket (stereo) mounting version</p>
Channels:	<p>Input channel: 2 x stereo with line-phono switch via RCA, channel control via fader, 3-band tone control EQ, gain control, CUE switch, source selector, CUE switch</p> <p>Input channel: 1 x stereo with line-player switch via RCA or player, channel control via fader, 3-band tone control EQ, gain control, CUE switch</p> <p>Microphone channel: 1 x mono via jack, channel control via rotary dial, 2-band tone control EQ, ON AIR switch</p> <p>Master output: 1 x stereo via RCA, channel control via rotary dial, cue mix function</p> <p>Headphones output: 1 x stereo via jack, channel control via rotary dial</p>
Music format:	MP3, WAV
Available storage media:	USB devices max. 32GB (FAT 32)
USB port:	Type A
Housing design:	Desktop console housing
Dimensions:	<p>Width: 17.2 cm</p> <p>Depth: 26 cm</p> <p>Height: 7.8 cm</p>
Weight:	1.83 kg

Scope of delivery:

- 1 x mixer
- 1 x user manual
- 1 x external mains adapter