

## OMNITRONIC EM-550B MK2 Entertainment Mixer

Multifunctional 5+2-channel installation mixer, black

Art. No.: 10007103

GTIN: 4026397714333



### Features:

- 5 input channels with recessed gain controls on the rear panel, signal LED and smooth channel faders
- Prefader listening to input channels and the master output via adjustable headphones output, with cue mix/split function
- 2 adjustable master outputs with 3-way equalizer and 10-digit stereo LED level meter
- (19") 48.3 cm rack installation 2 U
- For application areas such as: Installation; restaurants, bars and hotels; clubs/dancing school

### Logistic

EAN / GTIN: 4026397714333

Weight: 3,46 kg

Length: 0.50 m

Width: 0.14 m

Height: 0.18 m

### Technical specifications:

Power supply:	230 V AC, 50 Hz
Power consumption:	9 W
Protection class:	Protection class II
Power connection:	Power supply cord with Euro plug (provided)
Frequency range:	20 - 20000 Hz
S/N ratio:	>65 dB line/phono
THD:	Line/phono <0.02 % at 1 kHz
Gain:	Microphone 52 dB Line 19 dB Phono 54 dB

Housing color:	Black
Control elements:	Power switch, regular talkover, source selector
Status LED:	Signal, master level meter, peak, channel source; CUE, talkover, ON AIR, routing
Connections:	<p>Input: microphone via 2 x 3-pin XLR/6.35mm jack (F) combination socket (mounting version)</p> <p>Input: line/phono via 2 x stereo RCA</p> <p>Input: line via 9 x stereo RCA</p> <p>Output: master via 2 x 3-pin XLR</p> <p>Output: master via 2 x stereo RCA</p> <p>Output: headphones via 1 x 6.3-mm-jack (bal.)</p> <p>Output: booth via stereo RCA</p> <p>Output: rec. via 2 x stereo RCA</p>
Channels:	<p>Input channel: 2 x stereo with line-line/phono switch via RCA, channel control via fader, , gain control, source selector, CUE switch</p> <p>Input channel: 3 x stereo with line-line switch via RCA, channel control via fader, , gain control, source selector, CUE switch</p> <p>Microphone channel: 2 x mono via Combination socket (XLR/jack), channel control via rotary dial, 3-band tone control EQ, ON AIR switch, talkover switch</p> <p>Master output: 2 x stereo via XLR or RCA, channel control via rotary dial, 3-band tone control EQ</p> <p>Rec. output: 2 x stereo via RCA, NO MIC switch</p> <p>Headphones output: 1 x stereo via jack, channel control via rotary dial, cue mix split function</p> <p>Booth output: 1 x mono + stereo via RCA, channel control via rotary dial</p> <p>Input channel: 1 x stereo via RCA, channel control via rotary dial</p>
Housing design:	(19") 48.3 cm rack installation 2 U
Dimensions:	<p>Width: 48.3 cm</p> <p>Depth: 14.8 cm</p> <p>Height: 8.9 cm</p>
Weight:	3.10 kg

### Scope of delivery:

1 x mixer  
 1 x user manual  
 1 x power cord  
 1 x RCA cable