

## **OMNITRONIC EM-650B MK2 Entertainment Mixer**

Multifunctional 5+2-channel mixer with 3 zones, black

**Art. No.: 10007113** GTIN: 4026397714326











**List price: 474.81 €** 

incl. 19% VAT.

## Features:

- 5 input channels with recessed gain controls on the rear panel, signal LED and smooth channel fadors
- 3 adjustable master outputs with 3-way equalizer and 10-digit stereo LED level meter
- (19") 48.3 cm rack installation 2 U
- For application areas such as: Installation; restaurants, bars and hotels; Clubs/dancing school Package contents
- 1 x mixer, 1 x user manual, 1 x power cord, 1 x rCA cable

## Logistic

EAN / GTIN: 4026397714326

Weight: 3,46 kg Length: 0.50 m Width: 0.14 m Heigth: 0.18 m

## **Technical specifications:**

| Power supply:     | 230 V AC, 50 Hz                               |
|-------------------|---|
| Protection class: | Protection class II                           |
| Power connection: | Power supply cord with Euro plug (provided)   |
| Frequency range:  | 20 - 20000 Hz                                 |
| S/N ratio:        | >60 dB line<br>>70 dB phono                   |
| THD:              | Line/phono <0,02 % at 1 kHz                   |
| Gain:             | Microphone 52 dB<br>Line 17 dB<br>Phono 53 dB |
| Housing color:    | Black   |

| Zone output:      | 3 adjustable zones  |
|-------------------|---|
| Control elements: | Power switch, regular talkover, source selector   |
| Status LED:       | Signal, chanal level meter, master level meter, peak, chanal source; CUE, Talkover, ON AIR, Routing   |
| Connections:      | Input: Microphone via 2 x 3-pin XLR/6.35mm jack (F) combination socket (mounting version)   |
|                   | Input: line/phono via 2 x stereo RCA  |
|                   | Input: line via 8 x stereo RCA  |
|                   | Output: master via 3 x 3-pin XLR  |
|                   | Output: master via 3 x stereo RCA   |
|                   | Output: rec. via 2 x stereo RCA   |
|                   | Output: headphones via 1 x 6.3-mm-jack (bal.)   |
| Channels:         | Input chanel: 2 x stereo with Line-Line/Phono switch via RCA, channel control via fader, 3-band tone control EQ, Routing master bus switch, gain control, source selector, CUE switch |
|                   | Input chanel: 3 x stereo with Line-line switch via RCA, channel control via fader, Routing master bus switch, gain control, source selector, CUE switch                               |
|                   | Microphon chanal: 2 x mono via Combination socket (XLR/jack), channel control via Rotary dial, ON AIR switch, Routing master bus switch, Talkover switch                              |
|                   | Master output: 3 x stereo via XLR or RCA, channel control via Rotary dial, 3-band tone control EQ   |
|                   | Rec. output: 1 x stereo via RCA, Routing master bus switch  |
|                   | Headphones output: 1 x stereo via Jack, channel control via Rotary dial, Cue-mix-function   |
| Housing design:   | (19") 48.3 cm rack installation 2 U   |
| Dimensions:       | Width: 48,3 cm  |
|                   | Depth: 14,8 cm  |
|                   | Height: 8,9 cm  |
| Weight:           | 3,10 kg   |