

## INTUSONIC HZE11 Zone Remote Control Panel

Flush-mount volume control, RS485, incl. IR remote control

Art. No.: 12604189

GTIN: 5060502923301



### Description:

The INTUGRID HZE11 provides a local control frontend for Intusonic's RS-485 enabled audio control systems, and by the nature of its user interface is the perfect complement for the HMA7x series of audio routers. It fits wall box sizes with minimal depth (86 mm) and hence can be mounted right where it is needed - in the room to be controlled. A standard CAT network cable is sufficient for connections; no additional power supply is required. Due to its daisy-chaining possibilities, more than one unit can be installed in a room, with the last operated one setting the system, and those settings being replicated on all HZE11 panels as well as the connected main unit. A local audio feed is possible via the provided 3.5mm jack for a stereo signal or alternatively via a 6.35mm jack for a mono microphone. For enhanced convenience, the HZE11 also sports an infrared remote control receiver and comes with a IRB44 remote control right out of the box.

### Features:

- Flush mounting
- Multiple units can be linked
- Control via IR remote control
- LCD display
- For further information about this product, please refer to the Data Sheet under "Downloads"

### Technical specifications:

Power supply: 12V DC

IP classification: IP20

### Logistic

EAN / GTIN: 5060502923301

Weight: 0,32 kg

Length: 0.11 m

Width: 0.10 m

Height: 0.06 m

Control:	IR remote control
Housing color:	Black
Display type:	LCD display
Connections:	Input: line via 3.5 mm jack (stereo) Input: microphone via 6.3 mm jack socket (mono) mounting version RS 485 via RJ-45 (F) mounting version
Mounting depth:	30 mm
Housing design:	Flush mounting
Dimensions:	Width: 8.6 cm Depth: 8.6 cm Height: 4.2 cm
Weight:	0.28 kg

### **Scope of delivery:**

---

- 1 x device
- 1 x remote control
- 1 x battery
- 6 x screw
- 1 x cover
- 1 x user manual