

OMNITRONIC Airbro 5.8G Jack Receiver

Plug-n-play wireless audio receiver

Art. No.: 13072341

GTIN: 4026397672398



List price: 53.43 €

incl. 19% VAT.

Features:

- Replaces the cable between instrument and guitar amplifier
- Enjoy freedom of movement during live performance
- Convenient and quickly ready for use thanks to one-button operation
- Operation in the interference-free 5.8 GHz band
- 24 bit/48 kHz for the ultimate sound quality
- 4 switchable transmission channels
- Several receivers can be coupled with a single transmitter
- Angle adjustable by 180°, therefore suitable for all guitar types
- Battery operation up to 4h
- 5.8 GHz license-free worldwide
- Operating range up to 15m in buildings
- Operating range up to 30m in the open air
- Ultra-low latency
- Up to 4 transmitters can be operated in parallel without interference

Package contents

- 1 x device, 1 x user manual, 1 x USB cable, 1 x screwdriver, 1 x bag

Logistic

EAN / GTIN: 4026397672398

Weight: 0,12 kg

Length: 0.14 m

Width: 0.09 m

Height: 0.04 m

Technical specifications:

Type:	Receiver
Battery pack type:	1 x lithium ion 400 mAh,
Battery pack:	Battery operation up to 4h Recharging time 2h

Frequency range:	20 - 20000 Hz
Range:	Range up to 15m in buildings Range up to 30m in the open air
Frequency band:	5.8 GHz
Parallel mode:	Max. 4 transmitter
Latency:	< 6 ms
Status LED:	Charge status indicator
Connections:	Output: 6.3 mm plug (unbal.)
Max. level:	Output: +770 mV, unbal.
USB port:	Typ micro USB (F) mounting version
Dimensions:	Width: 13,8 cm Depth: 2,7 cm Height: 4,3 cm
Weight:	90 g