



List price: 593.81 €

incl. 19% VAT.

Features:

EUROLITE LED B-40 HCL Beam Effect MK2

LED beam effect with RGBWA+UV color mixing, incl. remote-control

- 5 powerful LEDs 10 W 6in1 HCL RGBWA/UV
 segments controlled separately
- 8 integrated show programs
- Control via IR remote control; stand-alone; Sound to light via Microphone; DMX; QuickDMX via USB (optional); W-DMX by wireless solution via USB (optional); CRMX by LumenRadio via USB (optional); Master/slave function
- Multi beam effect; Strobe effect
- With Omega bracket
- Monochrome 4 digit 7-segment LED display
- Rotation speed adjustable; Dimmer electronic; color blend stepless
- Preprogrammed in Light J; Light Captain; EASY SHOW 2; EASY SHOW 3
- For application areas such as: Clubs/dancing school; Wedding/gala/events; mobile djs / entertainer; restaurants, bars and hotels
- Application possibility: Standing; suspended

Package contents

- 1 x light effect, 1 x user manual, 1 x power cord, 1 x omega bracket, 4 x screw, 4 x washer, 1 x remote control, 1 x battery

Logistic

EAN / GTIN: 4026397718379

Weight: 15,00 kg

Length: 0.00 m

Width: 0.00 m

Height: 0.00 m

ROADINGER Flightcase 1x B-40 HCL/Laser

Trunk case, PRO version

- High-quality workmanship with birch multiplex 6,5 mm, dark brown
- Interior with foam padding
- Aluminum profile frames 20mm with rounded edges

- Hinged, chromium plated case handle
- 2 chrome tip-over locks
- 2 high-quality spring locks
- Branded hardware
- European engineering
- For further information about this product, please refer to the Data Sheet under "Downloads"

Technical specifications:

Weight: 11,12 kg

EUROLITE LED B-40 HCL Beam Effect MK2

Power supply:	100-240 V AC, 50/60 Hz
Power consumption:	56 W
IP classification:	IP20
Protection class:	Protection class I
Power connection:	Mains input via IEC connector (M) mounting version power supply cord with safety plug (provided)
Power output:	IEC connector (F) mounting version
Fuse:	T 1,6 A Fuse replaceable
Lamp type:	LED lamp
LED:	5 x 10 W 6in1 HCL RGBWA/UV
Flash rate:	0 - 20 Hz
DMX channels:	3; 12; 23
DMX input:	1 x 3-pin XLR (M) mounting version
DMX output:	1 x 3-pin XLR (F) mounting version
Control:	IR remote control; stand-alone; Sound to light via Microphone; DMX; QuickDMX via USB (optional); W-DMX by wireless solution via USB (optional); CRMX by LumenRadio via USB (optional); Master/slave function
Preprogrammed in:	Light J; Light Captain; EASY SHOW 2; EASY SHOW 3
Housing color:	Black
Attachment system:	Omega bracket
Display type:	Monochrome 4 digit 7-segment LED display
Dimensions:	Length: 32,00 cm Width: 32,00 cm Height: 39,00 cm
Weight:	4,22 kg
Noise classification:	Class 2 (slight noise)
Remote control	
Battery:	1 x Button cell 3.0 V CR2025 lithium manganese built-in

Legal specifications

Special product:	Not designed for household room illumination
Intended use:	Show effect lighting

ROADINGER Flightcase 1x B-40 HCL/Laser

Maximum load:	25 kg
Aluminum profile frames:	20 mm
Case handle:	1 pc/pcs
Stop hinge:	2 pc/pcs
Lock:	Spring lock: 2 pc/pcs
Use of brands:	Branded hardware
Material:	Birch multiplex, 6,5 mm, laminated
Color:	Dark brown
Device compartment:	32,5 cm x 32,5 cm x 39 cm
Dimensions:	Length: 40 cm Width: 40 cm Height: 48 cm
Weight:	6,90 kg