

## **EUROLITE LED PMC-16x20W COB 3200K**

PRO COB performance cluster with 4 x 4 matrix

Art. No.: 41606200

GTIN: 4026397459838











# The article is no longer in our assortment.

#### Features:

- Equipped with 16 x 20 W COB LED
- 3200 K color temperature
- 3, 16 or 19 DMX channels selectable for various applications
- Each LED can be controlled individually
- Functions: built-in programs and strobe effect with variable speed, dimmer, Master/Slave
- DMX-controlled operation or stand-alone operation with Master/Slave function
- For use on stages, catwalks, crossbeam systems, or decoration
- Comfortable addressing and setting via control panel with LC display and four operating buttons
- Locking possibility at the mounting bracket
- Power connection via Neutrik PowerCon jack and included power cable
- Feed-through output allows to power another device
- After every 8 device the fixtures must have a renewed connection with the power mains
- DMX control via every standard DMX controller
- Control via stand-alone; DMX; Sound to light via Microphone
- Preprogrammed in LED PC-Control 512; Light Captain
- With a beam angle of 60°

## **Technical specifications:**

Power supply:	100-240 V AC, 50/60 Hz
Power consumption:	275 W
IP classification:	IP20
Lamp type:	LED lamp

### Logistic

EAN / GTIN: 4026397459838

Weight: 9,20 kg Length: 0.43 m Width: 0.41 m Heigth: 0.26 m

Color temperature:	3200K
Flash rate:	1 - 20 Hz
DMX channels:	3; 16; 19
Control:	Stand-alone; DMX; Sound to light via Microphone
Preprogrammed in:	LED PC-Control 512; Light Captain
Beam angle:	60°
Beam angle (1/2 peak):	60°
Housing color:	Black
Dimensions:	Width: 31,5 cm
	Depth: 34,5 cm
	Height: 34,5 cm
Weight:	8,20 kg
DMX channels:	3/16/19
DMX connection:	5-pin and 3-pin XLR
Flash-rate:	20 Hz
Sound-control:	via built-in microphone
LED number:	16
LED type:	Array 20 W, white
Color temperature:	3200 K
Beam angle:	60°
Dimensions (W x D x H):	345 x 315 x 345 mm
Legal specifications	
Special product:	Not designed for household room illumination
Intended use:	Show effect lighting