

EUROLITE LED PMC-16x30W COB RGB WFL

PRO COB performance cluster (4 x 4 matrix) with 60° beam angle

Art. No.: 41606400

GTIN: 4026397459852



The article is no longer in our assortment.

Features:

- Equipped with 16 x 30 W COB LEDs in the colors red, green and blue
- 3, 5, 48 or 51 DMX channels selectable for various applications
- Each LED can be controlled individually
- Switch-mode power supply, automatic power supply adaption between 100 and 240 Volts without power selector
- Functions: static colors; RGB color mixture, automatic color change, built-in programs and strobe effect with variable speed, dimmer, Master/Slave
- DMX-controlled operation or stand-alone operation with Master/Slave function
- Comfortable addressing and setting via control panel with LC display and four operating buttons
- Locking possibility at the mounting bracket
- Power connection via Neutrik PowerCon jack and included power cable
- Feed-through output allows to power another device
- After every 8 device the fixtures must have a renewed connection with the power mains
- DMX control via every standard DMX controller
- Control via DMX; sound to light via microphone
- Preprogrammed in Light´J; Light Captain

Logistic

EAN / GTIN: 4026397459852

Weight: 9,50 kg

Length: 0.44 m

Width: 0.41 m

Height: 0.25 m

Technical specifications:

Power supply:	100-240 V AC, 50/60 Hz
Power consumption:	470 W
IP classification:	IP20
Power output:	1 x PowerCON (gray), mounting version

Lamp type:	LED lamp
Flash rate:	1 - 20 Hz
DMX channels:	3
Control:	DMX; sound to light via microphone
Preprogrammed in:	Light'J; Light Captain
Beam angle (1/2 peak):	60°
Housing color:	Black
Dimensions:	Width: 18 cm Depth: 37 cm Height: 35 cm
Weight:	8,5 kg
DMX channels:	3/5/48/51
DMX connection:	5-pin and 3-pin XLR
Flash-rate:	20 Hz
Sound-control:	via built-in microphone
LED number:	16
LED type:	Cluster 30 W, RGB
Beam angle:	60°
Dimensions (W x D x H):	350 x 180 x 370 mm
Legal specifications	
Special product:	Not designed for household room illumination
Intended use:	Show effect lighting