

EUROLITE LED ML-56 COB CW/WW 100W Floor sil

ML spot with 100 W COB LED in cold and warm white

Art. No.: 41607371

GTIN: 4026397565782



The article is no longer in our assortment.

Features:

- Equipped with a 100 W LED in CW/WW
- Functions: CW/WW color mixture, dimmer and strobe effect with adjustable speed
- Dimmer speed (step response) adjustable
- DMX-controlled operation or stand-alone operation with Master/Slave function
- Beam angle 35°
- Addressing and setting via Control Board with LED display and four operating buttons
- Ideal as floor spot via additional bracket
- Locking possibility at the brackets
- With color filter frame
- Optional barndoors available
- Ready for connection with power cord and safety plug
- Switch-mode power supply for operation between 100 and 240 Volts
- Available in silver or in black
- 1 powerful LED 100 W COB (chip-on-board) 2in1 BCL CW/WW (homogenous color mix)
- Strobe effect
- Control via DMX
- Preprogrammed in Light´J; LED PC-Control 512
- Flicker-free
- With a beam angle of 35°
- Good color rendering index (CRI)

Package contents

- 1 x filter frame

Logistic

EAN / GTIN: 4026397565782

Weight: 4,25 kg

Length: 0.28 m

Width: 0.28 m

Height: 0.38 m

Technical specifications:

Power supply:	100-240 V AC, 50/60 Hz
Power consumption:	90 W
IP classification:	IP20
Power connection:	Fixed power supply cord with safety plug
Lamp type:	LED lamp
LED:	1 x 100 W COB (chip-on-board) 2in1 BCL CW/WW (homogenous color mix)
DMX channels:	4
Control:	DMX
Preprogrammed in:	Light J; LED PC-Control 512
Projection:	Flicker-free
Beam angle:	35°
Beam angle (1/2 peak):	35°
Beam angle (1/10 peak):	74°
Color rendering index (CRI):	81 Ra
Housing color:	Silver
Dimensions:	Width: 29 cm Depth: 25,5 cm Height: 32 cm
Weight:	3,60 kg
DMX channels:	4
DMX connection:	3-pin XLR
Flash-rate:	17 Hz
LED number:	1
LED type:	Array Cluster 100 W, CW/WW
Color temperature:	2900-6000 K
Beam angle:	35°
Dimensions (L x W x H):	255 x 290 x 320 mm
Legal specifications	
Special product:	Not designed for household room illumination
Intended use:	Show effect lighting