

EUROLITE Dynamic Fog 1500 Flex Fog Machine

DMX machine with 1500 W power, adjustable output angle, timer and remote

Art. No.: 51702045

GTIN: 4026397549621



The article is no longer in our assortment.

Features:

- Concentrated and steady fog output
- Ideal for accentuating light and laser beams
- Vertically adjustable output angle for a perfect fog distribution
- Continuous output
- Adjustable timer with interval, duration and output volume
- Fan grille with blue LED illumination, switchable
- Short warm-up time
- Output distance: Approx. 5 m
- Control via DMX; Wireless remote control; wired remote control
- Preprogrammed in LED PC-Control 512; Light Captain
- With Mounting bracket
- For application areas such as: Clubs/dancing school; Stage
- With level indication
- Operates on water-based fluid
- Removable tank

Package contents

- 1 x device, 1 x user manual, 1 x power cord, 2 x remote control, 1 x declaration of conformity, 1 x container, 1 x filter, 1 x battery

Logistic

EAN / GTIN: 4026397549621

Weight: 12,50 kg

Length: 0.60 m

Width: 0.36 m

Height: 0.32 m

Technical specifications:

Power supply: 230 V AC, 50 Hz

Power consumption: 1500 W

IP classification: IP20

Power connection:	Mains input via IEC connector (M) mounting version power supply cord with safety plug (provided)
Warm-up time:	Approx. 4,5 min
Output volume:	Approx. 430 m ³ /min
Output distance:	Approx. 5 m
Tank capacity:	3,0 l water-based fluid removable tank
Fluid consumption:	Approx. 90 ml/min
DMX channels:	1
DMX input:	1 x 3-pin XLR (M) mounting version 1 x 5-pin XLR (M) mounting version
DMX output:	1 x 3-pin XLR (F) mounting version 1 x 5-pin XLR (F) mounting version
Control:	DMX; Wireless remote control; wired remote control
Preprogrammed in:	LED PC-Control 512; Light Captain
Carrier frequency:	433,92 MHz
Housing color:	Black
Attachment system:	Mounting bracket
Controls:	Low fluid; overheat
Color:	Black
Dimensions:	Width: 31,5 cm Depth: 47,5 cm Height: 37 cm
Weight:	11,15 kg
Remote control	
Battery:	1 x 12 V LR27 alkaline manganese built-in