

ANTARI Z-1520 LED Spray Fogger

1500 W machine, extremely powerful vertical fog output with LED illumination

Art. No.: 51702618

GTIN: 4719850651688



Features:

- Powerful fogger with bright RGB LEDs and DMX interface
- Spectacular fog and lighting effects at the same time
- 8-second jet spray mode with maximum fog volume
- Adjustable timer with interval and duration
- Manual fog output
- 22 LEDs 3 W high-power R/G/B
- Strobe effect
- Output distance: Approx. 5 m
- Operates on water-based fluid
- Removable tank
- 15 integrated show programs
- Control via stand-alone; DMX; wireless remote control; timer; master/slave function
- Built with NEUTRIK connector
- For application areas such as: Stage; theater; rental
- Application possibility: Standing **remote control**
- Operating range up to 50m

Logistic

EAN / GTIN: 4719850651688

Weight: 12,40 kg

Length: 0.52 m

Width: 0.42 m

Height: 0.31 m

Technical specifications:

Power supply: 230 V AC, 50 Hz

Power consumption: 1550 W

IP classification: IP20

Protection class:	Protection class I
Power connection:	Mains input via PowerCON (blue), mounting version power supply cord with safety plug (provided)
Lamp type:	LED lamp
LED type:	22 x 3 W high-power R/G/B
Warm-up time:	Approx. 5 min
Output distance:	Approx. 5 m
Tank capacity:	2.4 l water-based fluid removable tank
Fluid consumption:	Approx. 150 ml/min
DMX channels:	8
DMX input:	1 x 3-pin XLR (M) mounting version 1 x 5-pin XLR (M) mounting version
DMX output:	1 x 3-pin XLR (F) mounting version 1 x 5-pin XLR (F) mounting version
Control:	Stand-alone; DMX; wireless remote control; timer; master/slave function
Carrier frequency:	433.92
Housing color:	Grey
Use of brands:	Built with NEUTRIK connector
Color:	Grey
Dimensions:	Width: 29.5 cm Depth: 41.8 cm Height: 21 cm
Weight:	10.90 kg
Noise classification:	Class 3 (clearly perceptible sounds)
Battery:	1 x 12 V LR27 alkaline manganese built-in
Range:	Range up to 50m

Scope of delivery:

1 x device
 1 x user manual
 1 x declaration of conformity
 1 x power cord
 1 x remote control
 1 x container
 1 x filter