

FUTURELIGHT WDS-G4 wireless DMX transmitter

Wireless DMX transmitter, 2.4 GHz

Art. No.: 51834017

GTIN: 4026397470581



The article is no longer in our assortment.

Features:

- Compact wireless DMX transmitter for the wireless transmission of up to 512 DMX channels
- Wireless DMX eliminates extensive cabling between DMX controller and the DMX-controlled units in lighting installations
- Due to AFHSS (Automatic Frequency Hopping Spread Spectrum) and TDMA (Time Division Multiple Access) technology, interference-free operation also alongside other WDS-G4 transmitters and wireless devices in the 2.4 GHz band (e.g. Wi-Fi and Bluetooth)
- Operating range up to 200 m (with line-of-sight)
- Simultaneous operation of up to 16 transmitters, thus control of 8192 DMX channels (16 DMX universes) possible
- 1 to 512 receivers WDR-G4 can be controlled by each transmitter
- Transmission of RDM data
- Plug & Play: quick and easy setup with one operating button
- LED indication for operation and functions
- DMX input 5-pin XLR
- Powered via included PSU
- Battery operation (3 x AAA, not included)
- 2.4 GHz - license-free worldwide

Logistic

EAN / GTIN: 4026397470581

Weight: 0,47 kg

Length: 0.26 m

Width: 0.20 m

Height: 0.06 m

Technical specifications:

Dimensions: Width: 12,5 cm

Depth: 4,5 cm

Height: 7 cm

Dimensions (L x W x H): 125 x 70 x 45 mm

Weight:

130 g
