

## FUTURELIGHT WDR-G4 RX Wireless-DMX-Receiver

DMX wireless receiver with technology by Wireless Solution

Art. No.: 51834023

GTIN: 4026397588965



**The article is no longer in our assortment.**

### Features:

- Compatible with Wireless Solution W-DMX systems
  - Wireless DMX eliminates extensive cabling between DMX controller and the DMX-controlled units in lighting installations
  - AFHSS technology ensures interference-free operation also alongside other DMX transmitters and wireless devices in the 2.4 GHz band (e.g. Wi-Fi and Bluetooth)
  - 1 to 512 receivers can be controlled by each transmitter
  - Plug & play: quick and easy setup with one operating button
  - LED indication for operation and functions
  - DMX input and output, 3-pin XLR
  - Truss attachment option
  - 2.4 GHz - license-free worldwide
  - Can receive and process up to 512 DMX channels
  - Can transmit up to 512 DMX channels
  - Control via RDM; DMX; W-DMX by wireless solution
  - Operating range up to 500m with line-of-sight
  - 2.4 GHz license-free worldwide
  - Up to 6 transmitters can be operated in parallel without interference
  - Ultra-low latency
- Package contents**
- 1 x receiver, 1 x user manual, 1 x power cord, 1 x mounting bracket, 1 x antenna

### Logistic

EAN / GTIN: 4026397588965  
Weight: 1,15 kg  
Length: 0.21 m  
Width: 0.17 m  
Height: 0.10 m

### Technical specifications:

Power supply: 230 V AC, 50 Hz

Power consumption:	3 W
IP classification:	IP20
Power connection:	Mains input via P-Con (blue), mounting version power supply cord with safety plug (provided)
DMX channels:	Input 512 Output 512
DMX input:	1 x 3-pin XLR (M) mounting version
DMX output:	1 x 3-pin XLR (F) mounting version
Control:	RDM; DMX; W-DMX by wireless solution
Range:	Range up to 500m with line-of-sight
Frequency band:	2.4 GHz
Carrier frequency:	2,4 GHz
Parallel mode:	Max. 6 transmitter
Latency:	< 5 ms
Modulation:	AFHSS
Color:	Black
Dimensions:	Width: 14,5 cm Depth: 10 cm Height: 5,8 cm
Weight:	1,00 kg