

## **FUTURELIGHT CP-512 MST Controller 16 bit**

Universal DMX controller

Art. No.: 51834299 GTIN: 4026397280326











# The article is no longer in our assortment.

#### Features:

- 512 control channels for 16 projectors with up to 32 channels
- 16-bit resolution for fine Pan/Tilt movements
- Projector library with up to 255 entries
- 64 programs
- 64 records
- 64 preset scenes, 64 preset macros
- 10 selectable languages
- Mirror movement direction can be inverted
- Copy function for scenes, programs and records
- 99 chasers definable, one chaser per program
- Blackout function
- Sound control via built-in microphone or audio input
- Security code operation
- Operating hour meter
- USB port for firmware updates (available in the download section)
- Rack installation with 6 U
- Can transmit up to 512 DMX channels
- Control via DMX

### **Technical specifications:**

Power supply:	230 V AC, 50 Hz
Power consumption:	6,00 W
IP classification:	IP20

#### Logistic

EAN / GTIN: 4026397280326

Weight: 5,40 kg Length: 0.56 m Width: 0.34 m Heigth: 0.21 m

DMX channels:	Output 512
Control:	DMX
Housing color:	Black
Color:	Black
Dimensions:	Width: 48,3 cm Depth: 17,6 cm Height: 8,9 cm
Weight:	4,50 kg
	via 12 V DC, 500 mA power unit included in the delivery
Number of control channels:	512
Sound-input:	6.3 mm stereo Jack
Audio-sensitivity:	0.3-1 V
DMX512 output:	3-pin XLR connector
Free chasers:	64
Dimensions (LxHxD):	483 x 265 x 83 mm
	Rack installation with 6 u
Minimum mounting depth:	90 mm