

FUTURELIGHT DJ-Scan 260

Innovative DJ scanner with rotating gobos

Art. No.: 51839255 GTIN: 4026397220759











The article is no longer in our assortment.

Features:

- Strobe effect with adjustable speed (1-10 flashes/sec.) via separate shutter
- Strobe effect applicable with each color or gobo
- DMX-controlled operation or stand-alone operation with Master/Slave function (up to 4 slaves)
- Sound-controlled via built-in microphone
- Fuzzy sound control: program continues automatically during periods without music or bassbeat
- Blackout applicable in Stand Alone mode via optional FUTURELIGHT Easy-2 remote control
- Control board with 4-digit display
- Manual focus
- For MSD/HSD 250, MSD 250/2 or MSD/HSD 200 lamp
- DMX control via every standard DMX controller
- Gobo wheel with rotating gobos
- Color wheel with 7 dichroic filters plus open
Rainbow effect with adjustable speed in both directions
- Gobo wheel with rotating gobos, 7 gobos and open
- Control via Sound to light via Microphone

Technical specifications:

Power supply:	230 V AC, 50 Hz
Power consumption:	460 W
Flash rate:	1 - 10 Hz
Equipment:	Gobo wheel with rotating gobos

Logistic

EAN / GTIN: 4026397220759

Weight: 12,70 kg Length: 0.76 m Width: 0.35 m Heigth: 0.30 m

Color generation:	Color wheel with 7 dichroic filters plus open Rainbow effect with adjustable speed in both directions
Gobos:	Gobo wheel with rotating gobos, 7 gobos and open
DMX channels:	6
Control:	Sound to light via Microphone
Dimensions:	Width: 66,5 cm Depth: 26 cm Height: 29 cm
Weight:	11,05 kg
DMX channels:	6
DMX connection:	3-pin XLR
Sound-control:	via built-in microphone
Flash-rate:	10 Hz
Number of colors:	7 dichroic + white
Number of gobos:	7 rotating gobos and open
Dimensions (L x W x H):	665 x 260 x 290 mm
Legal specifications	
Special product:	Not designed for household room illumination
Intended use:	Show effect lighting