

## EUROLITE LED SLS-503 TCL 5x3W Floor

Slimline LED spot with 5 x 3 W 3in1 LED

Art. No.: 51915359

GTIN: 4026397514056



**The article is no longer in our assortment.**

### Features:

- Equipped with 3in1 tricolor LEDs for homogeneous light output in the colors red, green and blue
- Controllable via DMX, via control panel with LED display or via EUROLITE IR-4 Remote Control (51915279); not necessary for operating the unit and available optionally
- DMX512 control possible via any commercial DMX controller
- 3 or 5 DMX channels selectable for numerous applications
- Master/Slave function for synchronous operation with several devices
- The slave device is set via the IR-4 remote control
- Sound-control via built-in microphone
- Microphone-sensitivity adjustable
- Flat housing form requires minimal space when rigging
- Second mounting bracket for safe standing installation
- Additional rubber feet when the spot should be positioned on the floor without mounting bracket
- Power supply input and output and DMX input and output oppositely attached to the unit for easier wiring
- Comfortable addressing and setting via control panel with LED display
- Functions: Static colors, RGB color blend, internal programs, dimmer, strobe, sound-control
- Ready for connection via included IEC power cord with safety power plug
- Feed-through output allows to power up to 8 devices
- Switch-mode power supply for operation between 110 and 240 volts
- Preprogrammed in Light 'J'

### Logistic

EAN / GTIN: 4026397514056

Weight: 1,56 kg

Length: 0.24 m

Width: 0.24 m

Height: 0.15 m

### Technical specifications:

Power supply: 100-240 V AC, 50/60 Hz

Power consumption:	20,00 W
Preprogrammed in:	Light J
Dimensions:	Width: 24,4 cm Depth: 10,5 cm Height: 20,5 cm
DMX channels:	3/5
DMX connection:	3-pin XLR
Sound-control:	via built-in microphone
LED type:	3 W TCL
LED number:	5
Beam angle:	17.5°
Dimensions (W x D x H):	244 x 105 x 205 mm
Weight:	1 kg
Legal specifications	
Special product:	Not designed for household room illumination
Intended use:	Show effect lighting